

GEORGE C. MARSHALL SPACE FLIGHT CENTER
HUNTSVILLE, ALABAMA

Memorandum

TO : Mr. Jenke, JB-3
Through: ~~Mr. Kampmeier, R-ASTR-BV~~
9/28/11-10-66

FROM : Chief, Guidance and Control Systems
Analysis Branch, R-ASTR-NG

SUBJECT : Saturn V/501 open loop transient response study

DATE: November 10, 1966
In reply refer to:
R-ASTR-NG-156-66
ECSmith/vjd/876-4595

1. Purpose: This memorandum presents the results of the open loop transient response study of the Saturn V/501 flight control computers. The results are provided for information purposes in comparison with the pre-launch tests by JB.

2. Results: The results of these tests are shown in the enclosed Figures 2 through 27 for computer number 503. These curves are representative of the flight control computer number 504.

3. Test Arrangement:

a. The test arrangement for measuring the transient response in actuator motion (β) is shown in the enclosed Figure 1a. This arrangement consisted of the flight control computer, simulated valves and actuators, and an operational amplifier for isolation purposes.

b. The test arrangement for measuring the transient response in the output of the control computer (i_v) is shown in the enclosed Figure 1b. This arrangement consisted of the control computer operating into dummy loads, and an operational amplifier for isolation purposes.

4. Test Procedure: The actuator motion (β) and computer output (i_v) were recorded in response to a step input to the (ψ) and (ϕ) channels, respectively. Responses were obtained for each control gain for the inputs listed in the enclosed Table I. The table also includes the corresponding calculated steady-state outputs. The measured output values monitored on blockhouse recorders, should be within $\pm 20\%$ of the calculated steady-state values for i_v and β . This $\pm 20\%$ includes $\pm 10\%$ for a_0 and a_1 gains, and $\pm 10\%$ for the method of measurement and the measuring equipment.

3 Enc:
a/s

S. M. Seltzer
S. M. Seltzer

Approval:

F. B. Moore
F. B. Moore
Chief, Guidance and Control Division
MSFC - Form 488 (August 1960)

cc:

JB-3, Mr. Whiteside
JB-3, Mr. Terry
JB-33, Mr. Eli (5)
R-ASTR-N, Mr. Moore
R-ASTR-N, Mr. Gassaway
R-ASTR-NG, Dr. Seltzer
R-ASTR-NG, Mr. Brooks
R-ASTR-NGA, Mr. Drawe
R-ASTR-NGA, Mr. Kennel
R-ASTR-NGA, Mr. Schultz
R-ASTR-NGA, Mr. Roberts
R-ASTR-NGD, Mr. Chubb
R-ASTR-NGD, Mr. Brown
R-ASTR-NGD, Mr. Jones
R-ASTR-NCI, Mr. Blanton
R-ASTR-NCI, Mr. Scott (10)
R-ASTR-NCI, Mr. Nicaise
R-ASTR-NCI, Mr. E. C. Smith
R-ASTR-NF, Mr. Bridges (2)
~~R-ASTR-NC~~, Record file/Branch file
R-ASTR-X, Reference file

CLASSIFICATION

CENTERING GUIDE LINES

REPORT NO.


UNIT OF TYPING

FOR EMERGENCY USE ONLY


FIGURE 1

TEST ARRANGEMENT FOR OPEN LOOP TRANSIENT
RESPONSE STUDY

S-IC, S-II,& S-IVB STAGES



A. β ACTUATOR VERSUS STEP INPUT IN
 ψ OR ϕ CHANNEL.



B. i_v VERSUS STEP INPUT IN
 ψ OR ϕ CHANNEL.

TABLE I
INPUT AND OUTPUT SIGNALS FOR
CONTROL SYSTEM TRANSIENT RESPONSES


A. β RESPONSE


| FIGURE NO. | P | Y | |
|---|-------|-----------------------|-----------------------------------|
| 1. S-IC STAGE | INPUT | GAINS | STEADY-STATE OUTPUT CALCULATED |
| $\psi = 5^\circ$ (P&Y) $0 < T_f < 100$ | 0.82 | $\beta = 4.10^\circ$ | 2 2 |
| $\psi = 5^\circ$ (P&Y) $100 < T_f < \text{cutoff}$ | 0.45 | $\beta = 2.25^\circ$ | 2 2 |
| $\psi = 10^\circ$ (P) S-IC Burn | 0.245 | $\beta = 1.732^\circ$ | 3 3 |
| $\dot{\phi} = 5^\circ/\text{s}$ (P&Y) $0 < T_f < 100$ | 0.657 | $\beta = 2.63^\circ$ | 4 5 |
| $\dot{\phi} = 5^\circ/\text{s}$ (P&Y) $100 < T_f < \text{cutoff}$ | 0.438 | $\beta = 1.752^\circ$ | 4 5 |
| $\dot{\phi} = 10^\circ/\text{s}$ (R) S-IC Burn | 0.15 | $\beta = 1.061^\circ$ | 3 3 |
| 2. S-II STAGE | | | |
| $\psi = 5^\circ$ (P&Y) Ignition $< T_f < 60$ | 1.12 | $\beta = 5.60^\circ$ | 6 7 |
| $\psi = 5^\circ$ (P&Y) $60 < T_f < 190$ | 0.65 | $\beta = 3.25^\circ$ | 6 7 |
| $\psi = 5^\circ$ (P&Y) $190 < T_f < \text{cutoff}$ | 0.44 | $\beta = 2.20^\circ$ | 6 7 |
| $\psi = 10^\circ$ (P) S-II Burn | 0.25 | $\beta = 1.77^\circ$ | 8 8 |
| $\dot{\phi} = 4^\circ/\text{s}$ (P&Y) Ignition $< T_f < 60$ | 1.89 | $\beta = 7.56^\circ$ | 9 10 |
| $\dot{\phi} = 4^\circ/\text{s}$ (P&Y) $60 < T_f < 190$ | 1.10 | $\beta = 4.40^\circ$ | 9 10 |
| $\dot{\phi} = 4^\circ/\text{s}$ (P&Y) $190 < T_f < \text{cutoff}$ | 0.74 | $\beta = 2.96^\circ$ | 9 10 |
| $\dot{\phi} = 10^\circ/\text{s}$ (P) S-II Burn | 0.20 | $\beta = 1.414^\circ$ | 8 8 |
| 3. S-IVB STAGE | | | |
| $\psi = 5^\circ$ (P&Y) 1st S-IVB Burn | 0.809 | $\beta = 4.045^\circ$ | 11 12 |
| $\psi = 5^\circ$ (P&Y) 2nd S-IVB Burn | 0.809 | $\beta = 4.045^\circ$ | 11 12 |
| $\dot{\phi} = 4^\circ/\text{s}$ (P&Y) 1st S-IVB Burn | 0.970 | $\beta = 3.88^\circ$ | 11 12 |
| $\dot{\phi} = 4^\circ/\text{s}$ (P&Y) 2nd S-IVB Burn | 0.970 | $\beta = 3.88^\circ$ | 11 12 |
| Ignition $< T_f < 263.2$ | | | |
| $\dot{\phi} = 4^\circ/\text{s}$ (P&Y) 2nd S-IVB Burn | 0.698 | $\beta = 2.79^\circ$ | 11 12 |
| $263.2 < T_f < \text{cutoff}$ | | | |


Same as Figures 11 and 12 except redundant channel is used 13 14


TABLE I (CONT)


| B. i_v RESPONSES | | STEADY-STATE OUTPUT CALCULATED | FIGURE NO. | |
|--|-------|-----------------------------------|------------|----|
| 1. S-IC STAGE | INPUT | GAINS | P | Y |
| $\dot{\phi}=5^\circ(P&Y) \quad 0 < T_f < 100$ | 0.82 | $i_v = 39.69 \text{ ma}$ | 15 | 15 |
| $\dot{\phi}=5^\circ(P&Y) \quad 100 < T_f < \text{cutoff}$ | 0.45 | $i_v = 21.78 \text{ ma}$ | 15 | 15 |
| $\dot{\phi}=10^\circ/\text{s}(R) \quad \text{S-IC Burn}$ | 0.245 | $i_v = 16.77 \text{ ma}$ | 16 | 16 |
| $\dot{\phi}=5^\circ/\text{s}(P&Y) \quad 0 < T_f < 100$ | 0.657 | $i_v = 31.80 \text{ ma}$ | 17 | 18 |
| $\dot{\phi}=5^\circ/\text{s}(P&Y) \quad 100 < T_f < \text{cutoff}$ | 0.438 | $i_v = 21.20 \text{ ma}$ | 17 | 18 |
| $\dot{\phi}=10^\circ/\text{s}(R) \quad \text{S-IC Burn}$ | 0.15 | $i_v = 10.27 \text{ ma}$ | 16 | 16 |
| 2. S-II STAGE | | | | |
| $\dot{\phi}=5^\circ(P&Y) \quad \text{Ignition} < T_f < 60$ | 1.12 | $i_v = 35.17 \text{ ma}$ | 19 | 20 |
| $\dot{\phi}=5^\circ(P&Y) \quad 60 < T_f < 190$ | 0.65 | $i_v = 20.40 \text{ ma}$ | 19 | 20 |
| $\dot{\phi}=5^\circ(P&Y) \quad 190 < T_f < \text{cutoff}$ | 0.44 | $i_v = 13.82 \text{ ma}$ | 19 | 20 |
| $\dot{\phi}=10^\circ(R) \quad \text{S-II Burn}$ | 0.25 | $i_v = 11.10 \text{ ma}$ | 21 | 21 |
| $\dot{\phi}=4^\circ/\text{s}(P&Y) \quad \text{Ignition} < T_f < 60$ | 1.89 | $i_v = 47.48 \text{ ma}$ | 22 | 23 |
| $\dot{\phi}=4^\circ/\text{s}(P&Y) \quad 60 < T_f < 190$ | 1.10 | $i_v = 27.63 \text{ ma}$ | 22 | 23 |
| $\dot{\phi}=4^\circ/\text{s}(P&Y) \quad 190 < T_f < \text{cutoff}$ | 0.74 | $i_v = 18.59 \text{ ma}$ | 22 | 23 |
| $\dot{\phi}=10^\circ/\text{s}(R) \quad \text{S-II Burn}$ | 0.20 | $i_v = 8.88 \text{ ma}$ | 21 | 21 |
| 3. S-IVB STAGE | | | | |
| $\dot{\phi}=5^\circ(P&Y) \quad 1\text{st S-IVB Burn}$ | 0.809 | $i_v = 27.02 \text{ ma}$ | 24 | 25 |
| $\dot{\phi}=5^\circ(P&Y) \quad 2\text{nd S-IVB Burn}$ | 0.809 | $i_v = 27.02 \text{ ma}$ | 24 | 25 |
| $\dot{\phi}=4^\circ/\text{s}(P&Y) \quad 1\text{st S-IVB Burn}$ | 0.970 | $i_v = 25.92 \text{ ma}$ | 24 | 25 |
| $\dot{\phi}=4^\circ/\text{s}(P&Y) \quad 2\text{nd S-IVB Burn}$ | 0.970 | $i_v = 25.92 \text{ ma}$ | 24 | 25 |
| $\dot{\phi}=4^\circ/\text{s}(P&Y) \quad \text{Ignition} < T_f < 263.2$ | | | | |
| $\dot{\phi}=4^\circ/\text{s}(P&Y) \quad 2\text{nd S-IVB Burn}$ | 0.698 | $i_v = 18.65 \text{ ma}$ | 24 | 25 |
| $263.2 < T_f < \text{cutoff}$ | | | | |
| Same as Figures 24 and 25 except redundant channel is used | | | | 26 |
| | | | | 27 |

















FIG. 6

T_f

CURVES

| | |
|-----------------------|---|
| IGNITION < T_f < 60 | 1 |
| 60 < T_f < 190 | 2 |
| 190 < T_f < Cutoff | 3 |

YY 3Y

1

YY 3Y

2

YY 3Y

3

S-II STAGE
AS-501 CONTROL COMPUTER #503
OPEN LOOP RESPONSE
INPUT STEP = 5 deg.

$\beta - 1$ deg/sec

6

5

4

3

2

1

0

.2

.4

.6

.8

1.0

1.2

1.4

1.6

1.8

TIME (Seconds)

FIG. 7

S-II STAGE
 AS-501 CONTROL COMPUTER #503
 β OPEN LOOP RESPONSE
 ϕ INPUT STEP = 10 deg/sec
 ψ INPUT STEP = 10 deg.

| T_f | CURVES |
|-------------|----------|
| S - II BURN | 1,2,3,&4 |




FIG. 8

$\beta = 2 \text{ deg/in.}$

| T_f | CURVES |
|-----------------------|--------|
| IGNITION < T_f < 60 | 1 |
| 60 < T_f < 190 | 2 |
| 190 < T_f < Cutoff | 3 |

S-II STAGE
AS-501 CONTROL COMPUTER #503
P OPEN LOOP RESPONSE
D INPUT STEP = 4 deg/sec




FIG. 9

T_f CURVES


| | |
|-----------------------|---|
| IGNITION $< T_f < 60$ | 1 |
| $60 < T_f < 190$ | 2 |
| $190 < T_f <$ Cutoff | 3 |

S-II STAGE

AS-501 CONTROL COMPUTER #503

β OPEN LOOP RESPONSE

θ INPUT STEP = 4 deg/sec



T_f

CURVES

1 ST & 2 ND BURN

1


2 ND BURN

IGNITION $< T_f < 263.2$


2


$263.2 < T_f <$ Cutoff

3



$\rho = 1 \text{ deg/in.}$





T_f

CURVES

1 ST & 2 ND BURN

1

2 ND BURN


IGNITION $< T_f < 263.2$


2


$263.2 < T_f <$ Cutoff


3


$\theta = 1 \text{ deg/in.}$

















50

40

40

30

20

10

 $\dot{e}_v = 10 \text{ ma/in.}$ T_f

CURVES

| | |
|------------------------------|---|
| $\text{IGNITION} < T_f < 60$ | 1 |
| $60 < T_f < 190$ | 2 |
| $190 < T_f < \text{Cutoff}$ | 3 |




FIG. 19

$\Delta Y = 10 \text{ ms/in.}$

50

40

30

20

10

0

T_p

CURVES

IGNITION

T_p

60

1

60

T_p

190

2

190

T_p

Cutoff

3

S-II STAGE

AS-501 CONTROL COMPUTER #503

L OPEN LOOP RESPONSE

V INPUT STEP = 5 deg.

ΨY 3Y

1

ΨY 3Y

2

ΨY 3Y

3

FIG. 20

.2

.4

.6

.8

1.0

1.2

1.4

1.6

1.8

TIME (Seconds)

15

$$\zeta_r = 5 \text{ rad/in.}$$

T_f **CURVES**
S-II BURN 1, 2, 3&4

YR 4P

YR 4P

S-II STAGE

AS-501 CONTROL COMPUTER #503

(OPEN LOOP RESPONSE)

INPUT STEP = 10 deg/sec

INPUT STEP = 10 deg.

YR 3Y

YR 3Y


3


4

FIG. 21

.2 .4 .6 .8 1.0 1.2 1.4 1.6 1.8

TIME (Seconds)





T_f

CURVES

1 ST & 2 ND Burn

1

2 ND BURN

IGNITION $< T_f < 263.2$

2

$263.2 < T_f <$ Cutoff

3

V P IP

1

2

P IP

3

P IP

$i_v = 5 \text{ ma/in.}$

30

25

20

15

10

5

0

.2

.4

.6

.8

1.0

1.2

1.4

1.6

1.8

TIME (Seconds)

PRIME CHANNEL

FIG. 24

S-IVB STAGE

AS-501 CONTROL COMPUTER #503

i_v OPEN LOOP RESPONSE

\bullet INPUT STEP= 4 deg/sec

\times INPUT STEP= 5 deg.

