12 YEARS



GUIDANCE NAVIGATION

Changed by ... Chiley Date 1. Elassified Document Master Control Station, Scientific and Technical Information Facility CLASSIFICATION CHANGE To UNCLASS.
By authority

Approved:

Date: 6/16/64

MILTON B. TRAGESER, DIRECTOR APOLLO GUIDANCE AND NAVIGATION PROGRAM

Approved: 🖊

INSTRUMENTATION LABORATORY

E-1142 (Rev. 21) (UNCLASSIFIED TITLE)

SYSTEM STATUS REPORT

June 15, 1964





CAMBRIDGE 39, MASSACHUSETTS

COPY # 13 OF 150 COPIES THIS DOCUMENT CONTAINS 42 PAGES

REMOVE THIS

ACKNOW LEDGMENT

This report was prepared under DSR Project 55-191, sponsored by the Manned Spacecraft Center of the National Aeronautics and Space Administration through Contract NAS 9-153.

This document contains information affecting the national defense of the United States within the meaning of the Espionage Laws, Title 18, U.S.C., Sections 793 and 714, the transmission or the revelation of which in any manner to an unauthorized person is prohibited by law.

The publication of this report does not constitute approval by the National Aeronautics and Space Administration of the findings or the conclusions contained therein. It is published only for the exchange and stimulation of ideas.

LIST OF EFFECTIVE PAGES

Page Numbers

Title Page through vi

1-1

2-1 through 2-10

3-1 through 3-7

4-1 through 4-5

5-1 through 5-8

Distribution List

CONTENTS

Section		Page
1	INTRODUCTION	1-1
1-1	INTRODUCTION	1-1
1-2	ACCURACY	1-1
2	BLOCK I COMMAND MODULE DATA	2-1
2-1	WEIGHTS	2-1
2-1.1	WEIGHTS STATUS REPORTING	2-1
2-1.2	CONTROL WEIGHT	2-1
2-1.3	DESIGN LOAD WEIGHT	2-1
2-2	REPORTED WEIGHT CHANGES	2-6
2-2.1	OPTICAL SUBSYSTEM	2-6
2-2.2	OPTICAL EYEPIECES	2-6
2-2.3	IMU CONTROL PANEL, OPTICS COVER AND OPTICS SHROUD	2-6
2-3	CENTERS OF GRAVITY	2-6
2-4	MOMENTS OF INERTIA	2-6
2-5	BLOCK I (100-SERIES SYSTEMS)	2-6
2-6	COMMAND MODULE POWER REQUIREMENTS	2-7
3	BLOCK II COMMAND MODULE DATA	3-1
3-1	RELIABILITY	3-1
3-2	WEIGHTS	3-1
3-3	REPORTED WEIGHT CHANGES	3-1
3-3.1	OPTICAL EYEPIECES	3-1
3-3.2	OPTICAL SHROUD AND COVER	3-1
3-4	POWER REQUIREMENTS	3-4
3-5	STATUS OF COMMAND MODULE AGC PROGRAMS	3-7
4	LUNAR EXCURSION MODULE DATA	4-1
4-1	RELIABILITY	4-1
4-2	WEIGHTS FOR LEM	4-1
4-3	POWER REQUIREMENTS	4-3
E	CLOSSADY AND SYSTEM DEFINITION	51

DATE 6/15/64

ILLUSTRATIONS

Figure		Page
2-1	Electrical Load on Primary +28 VDC Power Supply	2-8
3-1	Electrical Load on Primary +28 VDC Power Supply	3-5
4-1	Electrical Load on Primary +28 VDC Power Supply	4-4
	TABLES	
Table		Page
2-I	Current Weight Status of Block I Command Module	2-2
2-II	Block I Command Module Center of Gravity and Moments of Inertia Data	2-4
2-III	Nominal Power Dissipation (watts) vs G&N Activity	2-9
2-IV	Block I Command Module Power Profile for 14-Day Lunar Orbit Mission	2-1
3-I	Reliability (as of 6/15/64)	3-1
3-II	Current Weight Status of Block II Command Module	3-2
3-III	Block II Command Module Power Profile for 14-Day Lunar Orbit Mission	3-6
3-IV	Current Memory Estimates and the Status of Command Module AGC Programs	3-7
4-I	Reliability (as of $6/15/64$)	4-1
4-II	Estimated Weights of LEM G&N Components	4-2
4-III	LEM Power Profile Based on LEM ICD LIS-390-3	4-5

ABSTRACT

The System Status Report is distributed monthly on the 15th. This month's revision (E-1142, Rev. 21) contains, in general, the following information for the Block I and Block II Command Module and LEM equipment configurations: weights, centers of gravity, moments of inertia, power requirements, status of computer programs, and reliability figures.

DATE 6/15/64

Section 1

INTRODUCTION

1-1 INTRODUCTION

The definition of what constitutes Block I and Block II Command Module and LEM hardware is contained in the Glossary, section 5 of this report.

The following information is included in this month's report:

- (1) Command Module, Block I: weights, centers of gravity, moments of inertia, power requirements, and a brief description of Block I (100-series systems).
- (2) Command Module, Block II: weights, power requirements, status of computer programs, and reliability figures.
- (3) LEM: weights, power requirements, and reliability figures.

1-2 ACCURACY

The accuracy of numerical values reported in this revision should not be considered to be within the tolerances implied by the significant figures quoted. The reported values, although based upon the most current information, are subject to normal changes as design and development phases approach completion.

BLOCK I

COMMAND MODULE

Section 2

BLOCK I COMMAND MODULE DATA

2-1 WEIGHTS

Table 2-1 presents the weights of all Block I equipment, grouped according to specific location within the Command Module. Weights are reported to the component level and to the nearest tenth of a pound.

Given component weights are identified as estimated, calculated, and measured in the order of increasing accuracy. These terms are defined by North American Aviation as follows.

Estimated weights (E) are based on rough calculations. Calculated weights (C) are based on detailed calculations made from final production drawings that will be used to build flyable equipment. Measured weights (M) are the actual weights of equipment built to the production drawings.

North American Aviation will provide and be responsible for cold plate weights that are not integral with guidance and navigation equipment.

- 2-1.1 WEIGHTS STATUS REPORTING. Table 2-I also offers a comparison of present component weight values with those listed in System Status Report, E-1142 (Rev. 20), May 15, 1964. All weight changes are explained in paragraph 2-2.
- 2-1.2 CONTROL WEIGHT. Column (a) in table 2-I contains the February 15, 1964 weight status of Apollo G&N Equipment. Column (a) adds up to approximately the total control weight specified in letter PG-64-113 (March 6, 1964) from Mr. D. Gilbert, ASPO, to Mr. M. Trageser, MIT/IL.
- 2-1.3 DESIGN LOAD WEIGHT. At NASA Coordination Meeting No. 15A, MIT agreed to assign "not-to-exceed" design load weights for individual Block I G&N subsystems. These weights were assigned by MIT in MIT letter AG 594-64, 18 May 1964, and are shown in column (d) of Table 2-I in this report. The total design load weight represents a secure maximum, since it is unlikely that the largest increases in each subsystem will occur simultaneously. The design loads listed recognize possible individual increases to account for changes accepted by NASA for the Block I flight systems (100-series systems). See paragraph 2-5.

DATE 6/15/64 PAGE 2-1

BLOCK I COMMAND MODULE

Table 2-I. Currer	Current Weight Status of Block I Command Module (lbs at 1	tus of Block	k I Command	1 Module (1b	s at 1 g)	
Item	Status 2/64		Status 5/64	,	Status 6/64	Design Load Wt.
	(a)	(b-a)	(q)	(c-b)	(c)	5/64 (d)
G&N SYSTEMS	; ;	•		•	6	, (
CDU Assy	14.5 (M)	-0.9	13.6 (M)	0.0	13.6 (M)	18.0
Optical Subsystem						
SXT	14.6(C)	+0.5	15.1(C)	, ,	1 6 0	
SCT	13.8 (C)	+0.5	14.3 (C)	7-0.2	46.2 (M) *	
Optical Base & Gearing	16.7(E)	+0.3	17.0(C)	<u> </u>		
Optical Eyepieces						√100.0
SXT	1.3(E)	0.0	1.3(E)	+0.3	1.6 (M) *	_
SCT	2.3(E)	0.0	2.3(E)	+0.3	2.6 (M) *	
NVB & Resilient Mounts	25.0(E)	0.0	25.0(E)	0.0	25.0 (E)	
Bellows Assy	13.5 (M)	0.0	13.5 (M)	0.0	13.5 (M)	
IMU	60.2 (M)	0.0	60.2 (M)	0.0	60.2 (M)	65.0
Coolant Hoses (two)	1.0(E)	-0.3	0.7(E)	0.0	0.7 (E)	
Power Servo Assy	59.4 (C)	+0.4	59.8 (C)	0.0	59.8 (C)	75.0
G&N Interconnection Assy	35.2 (E)	-5.2	30.0(C)	0.0	30.0 (C)	45.0
G&N to S/C Interface Assy	8.0 (E)	0.0	8.0(E)	0.0	8.0	0.001 ح
AGC (no spares)	70.0(E)	0.0	70.0(E)	0.0	70.0(E)	<u>-</u>
Optical Shroud	3.5 (M)	0.0	3.5 (M)	-0.4	3.1 (M)	4.5
LOWER EQUIPMENT BAY						
D&C						
D&C Electronics	2.9 (M)	0.0	2.9 (M)	0.0	·2.9 (M) —	
Control Electronics	2.9(E)	-0.9	2.0 (M)	0.0	2.0 (M)	
G&N Ind Cont Panel	9.5 (M)	+0.4	9.9 (M)	0.0	9.9 (M)	人 20.0
IMU Control Panel	2.4 (M)	0.0	2.4 (M)	+0.2	2.6 (M)	
MDV (includes 1 film)	7.7 (C)	+1.3	9.0 (M)	0.0	9.0 (M) *	
D&C/AGC	20.6 (M)	-0.2 +4.6	20.4 (M)	00	20. 4 (M) —	, ,
Signal Commercial Casay	7.7	2	7			

(Design Load Wt.**	5/64	(p)	0 96))			0.0		522.0							=	O, to		ıph 2–1.3.	
Current Weight Status of Block I Command Module (lbs at 1 g) (cont)	Status	6/64	(c)	20.4 (M)		1.5 (E)	2.5 (M) *	0.0 1.6 (M)		411.7		25.0(E)	34.6(E)	16.7 (E)	2.5(E)	0.3(E)	Monthly Center of Gravity Repor	Filbert, ASPO, to	,	See paragraph 2-1.3.	
Module (1bs			(c-b)	0.0		0.0	0.0	0.0		+0.1		0.0	0.0	0.0	0.0	0.0	Center of Gr			May 1964.	
Command 1	Status	5/64	(p)	20.4 (M)		1.5 (E)	2. 5 (M)	0.0 1.7 (M)	•	411.6		25.0(E)	34.6 (E)	16.7 (E)	2.5(E)	0.3(E)		6, 1964) fr		594-64, 18	
is of Block I			(b-a)	-0.1		0.0	+0.1	-3.6 0.0		-3.4		0.0	0.0	0.0	0.0	0.0	ion's "Apol	113 (March	12-1.2.	T letter AG	
Weight Statu	Status	2/64	(a)	20. 5 (M)		1.5 (E)	2.4(E)	3.6(E) 1.7 (M)		415.0**		25.0(E)	34.6(E)	16.7 (E)	2.5(E)	0.3(E)	nt Corpora	tter PG-64-	See paragraph 2-1.2.	en from MI	
Table 2-I. Current		Item		MAIN PANEL AREA D&C/AGC	LOOSE STORED ITEMS	Eye Relief Eyepieces	Film Cartridges (4)	Horizon Photometer Ontics Cover	•	TOTAL	List of Possible Spares for Block I	AGC Spare Logic Tray		PSA Spare (Unique) Modules	CDU Spare	Spare Relay & Diode Module	*Based upon Kollsman Instrument Corporation's "Apollo	**Control weight specified in letter PG-64-113 (March 6, 1964) from Mr. D.	Mr. M. Trageser, MIT/IL. S.	***Design Load Weights are taken from MIT letter AG 594-64, 18 May 1964.	

Veright (inches) Weight (inches) Momentary (i	Table 2-II. Block I Co	Block I Command Module Center of Gravity and Moment of Inertia Data	dule Cent	er of Grav	ity and Mc	ment of h	nertia Data	
Name		Weight	Cent	ers of Gra	vity	Мош	Moments of Inertia	ertia
Assy Assy al Subsystem T. t. Base & Gearing E. Resilient Mounts T. Assy T. T. T. Base & Gearing S. T. T. T. T. T. Base & Gearing S. T. T. T. T. T. T. T. T. T.	Item	(1bs)						
Assy al Subsystem T. t. Base & Gearing T. T			×	Y	Z	ľxx	Iyy	Izz
Assy al Subsystem T. T. A. Base & Gearing T. C. B. Besilient Mounts T. C. B. Be								
Assy al Subsystem T. T. t. Base & Gearing Solution and this and thoses 13.6 50.4* 60.2 56.6 0.0 41.7 60.2 56.6 0.0 41.7 41.3 41.3 44.8 Ather and this	LOWER EQUIPMENT BAY							
tr. Base & Gearing tr. Base & Gearing tr. Base & Gearing tr. Base & Gearing al Eyepieces Tr. & Resilient Mounts Tr. & Resilient Mounts Tr. tr. Base & Gearing and Fyepieces 50.4* 60.2 56.6 0.0 41.7 8.0 37.8 8.0 37.8 8.9 44.8 NAV Station U Cont Panel U Cont Panel 2.9 49.5 2.9 49.5 2.9 49.5 2.9 49.5 2.9 49.5 2.9 49.5 2.9 49.5 2.9 49.5 49.	CDU Assy	13.6	63.5	-14.4	35.8	73	144	131
tr. Base & Gearing tr. Base & Gearing tr. Base & Gearing T T 60.2 60.2 60.2 60.2 60.2 60.2 60.2 60.2 60.2 60.2 60.3 60.4 41.7 60.8 60.9 60.0 41.7 60.0 41.7 60.0 41.7 60.0 41.7 60.0 41.7 60.0 41.8 60.0 61.1 60.0 60	Optical Subsystem							
A. Base & Gearing 50.4^* 69.6 0.5 31.1 T. T	SCT							
## 69.6	Opt Base & Gearing		-		,			1
### Resilient Mounts ### Resilient Mounts ### Besilient Mounts #### Besilient Mounts ##### Besilient Mounts ##### Besilient Mounts ##### Besilient Mounts ##### Besilient Moun	Ontical Evenieces	50.4*	69.6	0.2	31.1	1468	992	1737
& Resilient Mounts 25.0 56.6 0.0 41.7 & Resilient Mounts 25.0 64.3 - 0.1 41.3 ows Assy 30.0 53.1 - 1.1 46.8 Interconnection Assy 8.0 37.8 8.9 44.8 Interconnection Assy 8.0 37.8 36.9 44.8 Interconnection Assy 8.0 37.8 36.9 44.8 Interconnection Assy 8.0 36.9 44.8 36.9 Interconnection Assy 8.0 37.8 14.8 36.9 Interconnection Assy 8.0 4.6 40.5 40.5 Interconnection Assy 8.0 4.6 9.5 40.5 Interconnection Assy 8.0 4.6 9.5 40.5 Interconnection Assy 8.9 4.6 9.5 40.5 Interconnection Assy	SXT					٠		
& Resilient Mounts 60.2 56.6 0.0 41.7 ows Assy 13.5 64.3 - 0.1 41.3 Interconnection Assy 30.0 53.1 - 1.1 46.8 to S/C Interface Assy 8.0 37.8 8.9 44.8 /NAV Station 2.6* 74.0 -15.4 30.9 /V Cont Panel 2.9 49.5 - 9.6 39.6 xC Electronics 2.9 49.5 - 9.6 39.6 ntrol Electronics Assy 2.0 63.1 10.7 34.9 trical Shroud & Cover 4.7* 66.8 0.0 28.9 kN Ind. Control Panel 9.9 54.1 0.1 33.9 /AGC 20.4 63.5 14.8 36.3 (no spares) 70.0 73.5 - 4.5 31.0 (no spares) 59.8 45.0 - 1.1 41.5 al Conditioner Assy 0.7 64.8 - 6.5 34.9 40.5 - 4.5 34.9 40.5 40.5 40.9 - 4.5 40.5 40.5	SCT				÷		···	
Assy 25.0 64.3 -0.1 41.3 Assy 30.0 53.1 -1.1 46.8 Assy 8.0 37.8 8.9 44.8 $2.6*$ 74.0 -15.4 30.9 2.9 49.5 -9.6 39.6 Assy 2.0 63.1 10.7 34.9 wer $4.7*$ 66.8 0.0 28.9 anel 9.9 54.1 0.1 33.9 20.4 63.5 14.8 36.3 9.0 73.5 -4.5 31.0 70.0 37.8 1.3 46.1 59.8 45.0 -1.1 41.5 Sy 4.6 49.8 9.5 40.5 0.7 64.8 -6.5 34.9	IMU	60.2	56.6	0.0	41.7	1186	1450	1438
Assy 30.0 53.1 - 1.1 46.8 Assy 8.0 37.8 8.9 44.8 2.6* 74.0 -15.4 30.9 2.9 49.5 - 9.6 39.6 Assy 2.0 63.1 10.7 34.9 wer 4.7* 66.8 0.0 28.9 30.9 54.1 0.1 33.9 20.4 63.5 14.8 36.3 9.0 73.5 - 4.5 31.0 70.0 37.8 1.3 46.1 59.8 45.0 - 1.1 41.5 59.8 46.0 5	NVB & Resilient Mounts	८5.0 →	6 7 3	<	41.2	2970	4050	5210
Assy 30.0 53.1 - 1.1 46.8 Assy 8.0 37.8 8.9 44.8 2.6* 74.0 -15.4 30.9 2.9 49.5 - 9.6 39.6 Assy 2.0 63.1 10.7 34.9 wer 4.7* 66.8 0.0 28.9 anel 9.9 54.1 0.1 33.9 20.4 63.5 14.8 36.3 9.0 73.5 - 4.5 31.0 70.0 37.8 1.3 46.1 59.8 45.0 - 1.1 41.5 sy 4.6 49.8 9.5 40.5	Bellows Assy	13.5 €	04.0	;	71.0	2	20	2
Assy 8.0 37.8 8.9 44.8 2.6* 74.0 -15.4 30.9 2.9 49.5 -9.6 39.6 3 Assy 2.0 63.1 10.7 34.9 over 4.7* 66.8 0.0 28.9 over 9.9 54.1 0.1 33.9 20.4 63.5 14.8 36.3 70.0 37.8 1.3 46.1 59.8 45.0 -1.1 41.5 3 sy 4.6 49.8 -6.5 34.9	G&N Interconnection Assy	30.0	53.1	- 1.1	46.8	3610	3110	4860
/NAV Station 2.6* 74.0 -15.4 30.9 IU Cont Panel 2.9 49.5 -9.6 39.6 LC Electronics 2.9 49.5 -9.6 39.6 Introl Electronics Assy 2.0 63.1 10.7 34.9 Actical Shroud & Cover 4.7* 66.8 0.0 28.9 LN Ind. Control Panel 9.9 54.1 0.1 33.9 /AGC 20.4 63.5 14.8 36.3 (Includes 1 film) 9.0 73.5 -4.5 31.0 (no spares) 70.0 37.8 1.3 46.1 al Conditioner Assy 4.6 49.8 9.5 40.5 ant Hoses 0.7 64.8 -6.5 34.9			37.8		44.8	378	403	32
U Cont Panel 2.6* 74.0 -15.4 30.9 LC Electronics 2.9 49.5 -9.6 39.6 nntrol Electronics Assy 2.0 63.1 10.7 34.9 tical Shroud & Cover 4.7* 66.8 0.0 28.9 tical Shroud & Cover 9.9 54.1 0.1 33.9 N Ind. Control Panel 9.9 73.5 -4.5 31.0 /AGC 20.4 63.5 14.8 36.3 (Includes 1 film) 9.0 73.5 -4.5 31.0 (no spares) 70.0 37.8 1.3 46.1 al Conditioner Assy 4.6 49.8 9.5 40.5 ant Hoses 0.7 64.8 -6.5 34.9	D&C/NAV Station							
LC Electronics 2.9 49.5 - 9.6 39.6 antrol Electronics Assy 2.0 63.1 10.7 34.9 brical Shroud & Cover 4.7* 66.8 0.0 28.9 LN Ind. Control Panel 9.9 54.1 0.1 33.9 AGC 20.4 63.5 14.8 36.3 / AGC 9.0 73.5 - 4.5 31.0 (no spares) 70.0 37.8 1.3 46.1 al Conditioner Assy 4.6 49.8 9.5 40.5 ant Hoses 0.7 64.8 - 6.5 34.9	IMU Cont Panel	2.6*	74.0	-15.4	30.9	15	22	24
tical Shroud & Cover 4.7* 66.8 0.0 28.9 tical Shroud & Cover 9.9 54.1 0.1 33.9 54.1 /AGC 20.4 63.5 14.8 36.3 / Includes 1 film) 70.0 37.8 1.3 46.1 59.8 45.0 - 1.1 41.5 al Conditioner Assy 4.6 49.8 9.5 40.5 ant Hoses 0.7 64.8 - 6.5 34.9	D&C Electronics	2.9	49.5	9.6 -	39.6	20	22	6
tical Shroud & Cover 4.7* 66.8 0.0 28.9 kN Ind. Control Panel 9.9 54.1 0.1 33.9 /AGC /AGC (Includes 1 film) 9.0 73.5 - 4.5 31.0 (no spares) 70.0 37.8 1.3 46.1 59.8 45.0 - 1.1 41.5 al Conditioner Assy 4.6 49.8 9.5 40.5 ant Hoses 0.7 64.8 - 6.5 34.9	Control Electronics Assy	2.0	63.1	10.7		6	15.	80
LN Ind. Control Panel 9.9 54.1 0.1 33.9 / AGC 20.4 63.5 14.8 36.3 7 (Includes 1 film) 9.0 73.5 - 4.5 31.0 (no spares) 70.0 37.8 1.3 46.1 59.8 45.0 - 1.1 41.5 al Conditioner Assy 4.6 49.8 9.5 40.5 ant Hoses 0.7 64.8 - 6.5 34.9	Optical Shroud & Cover	4.7*	8.99			387	108	413
/AGC 20.4 63.5 14.8 36.3 7 (Includes 1 film) 9.0 73.5 - 4.5 31.0 (no spares) 70.0 37.8 1.3 46.1 59.8 45.0 - 1.1 41.5 al Conditioner Assy 4.6 49.8 9.5 40.5 ant Hoses 0.7 64.8 - 6.5 34.9	G&N Ind. Control Panel	9.9	54.1	0.1		455	110	260
(Includes 1 film) 9.0 73.5 - 4.5 31.0 (no spares) 70.0 37.8 1.3 46.1 59.8 45.0 - 1.1 41.5 al Conditioner Assy 4.6 49.8 9.5 40.5 ant Hoses 0.7 64.8 - 6.5 34.9	D&C/AGC	20.4	63.5	14.8	36.3	294	1114	180
(no spares) 70.0 37.8 1.3 46.1 59.8 45.0 - 1.1 41.5 al Conditioner Assy 4.6 49.8 9.5 40.5 ant Hoses 0.7 64.8 - 6.5 34.9	MDV (Includes 1 film)	9.0	73.5		31.0	518	92	531
al Conditioner Assy 4.6 49.8 - 1.1 41.5 ant Hoses 0.7 64.8 - 6.5 34.9	AGC (no spares)	70.0	37.8	1.3	46.1	4980	3990	1710
4.6 49.8 9.5 40.5 0.7 64.8 - 6.5 34.9	PSA	59.8	45.0	- 1.1	41.5	3940	1460	2620
0.7 64.8 - 6.5 34.9	Signal Conditioner Assy	4.6	49.8		40.5	88	29	14
	Coolant Hoses	0.7	64.8	6.	34.9	-	∞	15

cont)

1 aure 2-11. Block I Com	ock I Command Module Center of Gravity and Moment of Inertia Data (cont)	le Center	of Gravity	and Mom	ent of Iner	tia Data (c	ont)
š	Weight	Cente	Centers of Gravity (inches)	vity	Mo	Moments of Inertia (1b-in)	ertia
Item	(ips)	×	*	Z	X		100
MAIN PANEL AREA D&C/AGC	20.4	67.8	-12.5	-20.4	283	256	317
Total Moments of Inertia About the Basic X, Y, Z Axes of the Command Module	407.6				681,030	1, 939, 064	1, 939, 0641, 308, 074
LOOSE STORED ITEMS Eye Relief Eyepieces Film Cartridges (4)	1.5	(SCT,	(SCT, 4-5/8" x 2 1/2" dia. (Each cartridge, 1-1/2 x 3	2 1/2" dia. 1-1/2 x 3		SXT 3" x 2-1/4" dia.) x 6 inches)	ia,)
List of Possible Spares for Block I AGC Spare Logic Tray AGC Spare Memory Tray PSA Loose Spares	25. 0 34. 6 16. 7	38.2	- 7.7	45.3	1290	1360	140
CDU Spare Gearbox Spare Relay & Diode Mod.	0.3	(approx (3 x 3 x	(approximately 6 (3 x 3 x 2 inches)	0 x 1-13	(approximately 6.0 x 1-13/16 x 5-1/2 inches) (3 x 3 x 2 inches)	inches)	
*These values represent changes since the last report, Rev. 20, dated May 15, 1964.	l since the la	l ast report,	l Rev. 20,	dated Ma	 y 15, 1964		

2-2 REPORTED WEIGHT CHANGES

- 2-2.1 OPTICAL SUBSYSTEM. The 0.2-pound weight decrease is the result of weighing the AGE 3 Optical Subsystem, reported in KIC's "Apollo Monthly Center of Gravity Report, dated 30 April 1964.
- 2-2.2 OPTICAL EYEPIECES. These weight changes are also based upon KIC's report, dated 30 April 1964 (see paragraph 2-2.1).
- 2-2.3 IMU CONTROL PANEL, OPTICS COVER AND OPTICS SHROUD. These weight changes are due to the weighing of AGE 5 equipment.

2-3 CENTERS OF GRAVITY

Table 2-II presents the centers of gravity of each weight component or packed assembly, determined with respect to the basic X, Y, Z, axes of the Command Module. Center of gravity values are given to the nearest tenth of an inch.

2-4 MOMENTS OF INERTIA

Table 2-II also presents the moment of the inertia of each weight component or packaged assembly, determined about each of the component axes which (1) run through the center of gravity of the component and (2), are parallel to the basic X, Y, and Z axes of the Command Module. The total moments of inertia of all G&N equipment (excluding loose stored items) have been calculated about the basic X, Y, Z, axes also.

2-5 BLOCK I (100-SERIES SYSTEMS)

The Block I weights reported in E-1142 have represented the basic Block I configuration. This configuration was not expected to be used for flight tests. All flight systems were to be Block II which would incorporate all changes necessary for flight. Recent scheduling decisions have made it necessary to use systems earlier than Block II for in-flight tests. Accordingly, a series of modifications to the basic zero-series Block I have been approved by NASA (Ref. MSC TWX No. E G04-17-64-208) to identify the 100-series Block I flight systems (previously called Block IF). The weight reporting for Block I this month is for the zero-series configuration. As the design details of the 100-series systems become firm, the Block I status reporting will begin to represent the 100-series systems.

Changes from zero-series to 100-series Block I G&N systems include: (1) addition of an horizon photometer and star tracker with associated electronics (2) a redesigned packaging of the flight computer, (3) modification of the electronics packaging to achieve moisture

BLOCK I COMMAND MODULE

proofing and to solve deficiencies in S&ID thermal interface material, (4) less flammable wiring insulation, and (5) addition of insulation to the cold surface.

2-6 COMMAND MODULE POWER REQUIREMENTS

The power requirements of the Command Module G&N equipment on the primary +28 VDC power supply are shown in figure 2-1, which presents the magnitude and location of dissipated power values on a subassembly level. This chart assumes a 14-day lunar orbit mission as defined by S&ID for power profile computation (Ref: S&ID letter 63 MA 7332).

Table 2-III shows the magnitude and location of power dissipation for the established G&N activities, each of which consists of various power levels of operation.

Table 2-IV shows the energy requirements for each G&N activity on a power level basis. The table is based upon MIT letter AG 679-6. "G&N Power Profile Status," dated August 14, 1963. The vertical column to the left indicates the various G&N activities (phases of operation) for the model 14-day mission submitted by S&ID in S&ID letter 63 MA 7332. The column also indicates the power requirement and operating time for each specific activity. The top row indicates the power requirement and operating time of each G&N power consuming equipment. The table sums up the energy consumptions for each G&N activity and each G&N power consuming equipment.

PAGE 2-7

BLOCK I

COMMAND MODULE




Figure 2-1. Electrical Load on Primary +28 VDC Power Supply

BLOCK I COMMAND MODULE

		Electrical Load	450.8	607.3	598.3	186.7	343.2	76.7	340.8	
	D&C.	and S&C	1	42.7	42.7	10	42	0	0.7	
Table 2-III. Nominal Power Dissipation (watts) vs G&N Activity	Thermal	Load On S/C Coolant	440.1	564.6	555.6	176.7	301.2	76.7	340.1	watts watts watts watts watts watts
ts) vs (AGC	110	110	110	110	110	10	10	120 1111.1 102.1 330.8 66.7 45.4
ion (wat	PSA	OBA	0	63.6	59.8	0	63.6	0	0	
issipati	Ā	IMU	233.5	233.5	233.5	41.2	41.2	41.2	233.5	10
ower D		CDU JB	22.1	44	44	0	21.9	0	22.1	T on T off te te y d Contr
minal P	NBA	OBA	0	39	33.8	Q	39	0	0	AGC Optics, SXT on Optics, SXT off IMU Operate IMU Standby Display and Control AGC Standby
III. No	Z	IMU	74.5	74.5	74.5	25.5	25.5	25.5	74.5	 AGC Optical Optical IMU IMU IMU IMU AGC
Table 2-	G&N Activity	(power levels)	IMU & AGC Operate (1, 4)	IMU Alignment (1, 2, 4, 6)	Low-Orbit Navigation (1, 3, 4, 6)	Standby & Computing (1, 5)	Midcourse Navigation (1, 2, 5, 6)	IMU & AGC Standby (5, 7)	IMU Operate & AGC Standby (4, 7)	·
	≱or	্ ভা	∢	В	ပ	Ω	ഥ	ĒΨ	ŗ	

BLOCK I

COMMAND MODULE

Comparate Computed Computed		Table	Table 2-IV. Block I Command Module Power Profile for 14-Day Lunar Orbit Mission	I Command M	lodule Power	Profile for 14	4-Day Lunar	Orbit Mission	ď	
6.805 1 0.984 0.911 6.391 0.672 6.391 1.239 1.147	35	N Activity	(1) AGC Operate 120 watts 84. 67 hrs	(2) Optics SXT on 111.1 watts 18.53 hrs	(3) Optics SXT off 102. 1 watts 3. 83 hrs	(4) IMU (5) IMU Operate Standby 330.8 watts 66.7 watts 76.09 hrs 260.32 hrs	(5) IMU Standby 66.7 watts 260.32 hrs	(6) Display & Controls 45.4 watts 22.36 hrs	(7) AGC Standby 10.0 watts 251.74 hrs	Total
0.984 0.911 0.459 0.391 1.239 1.147 1.339 1.147 1.40 1.147 1.50 1.	& A S	GC Operate tts, 56.71 hrs	6.805	1	1	18.759	1		1	25. 564
0.459 0.391 0.672 1.239 1.147 1.3 1.3 1.3 1.3	Alig 3 wa		0.984	0.911	1	2.712	1	0.372	-	4. 979
8 0.672 68 1.147 68 -	-Orb	it Navigation its, 3.83 hrs	0.459		0.391	1.266	1	0.173	ı	2.289
se Navigation 1.239 1.147 atts, 10.33 hrs AGC Standby tts, 244.39 hrs erate & AGC atts, 7.35 hrs	dby 6	c Computing	0.672		-	1	0.373	1	1	1.045
AGC Standby tts, 244.39 hrs erate & AGC atts, 7.35 hrs	cours	e Navigation tts, 10.33 hrs	1.239	1.147	1	1	0.689	0.468		3. 543
erate & AGC atts, 7.35 hrs	& A	GC Standby		-	-	1	16.300	1	2.443	18.743
	Ope 8 wa	rate & AGC tts, 7.35 hrs			-	2.431	1	1	0.073	2.504
TOTAL 10.159 2.058 0.391 25.	TOT		10.159	2.058	0.391	25.168	17.362	1.013	2.516	58. 667



Section 3

BLOCK II COMMAND MODULE DATA

3-1 RELIABILITY

The following numbers do not assume the use of in-flight spares or repair. The estimated Command Module G&N reliability is based on the 138-hour mission as defined in the Lunar Landing Mission Design Plan.

Table 3-I. Reliability (as of 6/15/64)

Subsystem	Operating Time (hrs) Full Power	Probability of Mission Success
IMU AGC (2) DSKY PSA CDU (5) Optics	31 19* 19 31* 31	0.99575 0.99988 0.999954 0.994 0.9942 0.9986
Total	G&N System	0.9825

^{*}Certain assemblies function continuously.

3-2 WEIGHTS

Table 3-II presents the weights of all Block II equipment. Refer to section 2-1 for a general explanation of weight reporting.

- 3-3 REPORTED WEIGHT CHANGES
- 3-3.1 OPTICAL EYEPIECES. See paragraph 2-2.2.
- 3-3.2 OPTICAL SHROUD AND COVER. See paragraph 2-2.3



Item	Status 2/64		Status 5/64		Status 6/64	Design Load Wt.
	(a)	(p-a)	(q)	(c-b)	(c)	3 / 6 4
G&N SYSTEMS	15 0 (15)	Φ +	99 0 (E)	<u> </u>	99 975)	
Optical Subsystem	(3)0.61	6.	(3) 6 . 77	•	(T) 6 - 77	
	18.2 (C)	+0.5	18.7(C)	0.0	18.7 (C)	
	13.8 (C)	+0.5	14.3(C)	0.0	14.3 (C)	
Optical Base & Gearing	16.7 (E)	+0.3	17.0(E)	0.0	17.0(E)	
Optical Eyepieces						
	1.3(E)	0.0	1.3(E)	+0.3	1.6(E)	
	2.3(E)	0.0	2.3(E)	+0.3	2.6(E)	
NVB & Resilient Mounts	22.0(E)	-4.0	18.0 (E)	0.0	18.0(E)	
Bellows Assy	13.5 (M)	0.0	13.5 (M)	0.0	13.5 (M)	
	42.0(E)	0.0	42.0(E)	0.0	42.0(E)	
Coolant Hoses (two)	1.0 (E)	-0.3	0.7 (E)	0.0	0.7(E)	
Power Servo Assy	41.6(E)	0.0	41.6(E)	0.0	41.6(E)	
G&N Interconnection Assy	35.2 (E)	-5.2	30.0(E)	0.0	30.0(E)	
G&N to S/C Interface Assy	8.0 (E)	0.0	8.0(E)	0.0	8.0 (E)	
complete computers)	84.0(E)	+4.0	88.0(王)	0.0	88.0(E)	•
Optical Shroud	3.5 (M)	0.0	3.5 (E)	-0.4	3.1(E)	
LOWER EQUIPMENT BAY				,		
D&C Flootman	1 5 (17)	-	1 5 (E)	•	1 5 (17)	
cri onica	(T) (C)	0 0	1:0(E)	> °	1.0(E)	
Control Electronics	2. 9 (E)	-0.9	2.0(E)	0.0	2.0(E)	
G&N Ind Cont Panel	11.1(E)	0.0	11.1(E)	0.0	11.1(E)	
MDV (includes 2 films)	8.3(E)	+1.3	9.6(E)	0.0	9. 6 (E)	
D&C/AGC	20.6(E)	-0.2	20.4(E)	0.0	20.4(E)	

CONFIDENTIAL

BLOCK II COMMAND MODULE

	Design Load Wt. 5/64 (d)				492.6**), to tph 2-1.3.
bs) (cont)	Status 6/64 (c)	20.4(E)	1.5(E) 1.9(E) 4.5(E) 3.5(E)	1. b (M)	400.0	Glbert, ASPO, to See paragraph 2-1.3.
nd Module (1	(c-b)	0.0	0.0	-0. I	+0.1	Mr. D.
k II Comma	Status 5/64 (b)	20.4(E)	1.5 (E) 1.9 (E) 4.5 (E) 3.5 (E)	1.7 (E)	399.9	3, 1964) from 2, February
Current Weight Status of Block II Command Module (lbs) (cont)	(b-a)	-0.1	0.0 +0.1 -4.0	0.0	-0.1	13, March 2-1.2. r 63 MA 203
nt Weight St	Status 2/64 (a)	20.5(E)	1.5(E) 1.8(E) 8.5(E) 3.5(E)	(च) । : ा	400.0* Control Weight	er (PG-64-113, M. paragraph 2-1.2. n S&ID letter 63 M ms.
Table 3-II. Curren	Item	MAIN PANEL AREA D&C/AGC	Eye Relief Eyepieces Film Cartridges (3) AGC Covers (2) PSA Cover	Optics Cover	TOTAL	*Control Weight specified in letter (PG-64-113, March 6, 1964) from Mr. M. Trageser, MIT/IL; See paragraph 2-1.2. **Design Load Weight taken from S&ID letter 63 MA 2032, February Does not include loose stored items.

BLOCK II COMMAND MODULE

3-4 POWER REQUIREMENTS

The power requirements of the Block II Command Module G&N equipment on the primary +28 VDC power supply are shown in figure 3-1, which presents the magnitude and location of dissipated power values on a subassembly level. This chart assumes a 14-day lunar orbit mission as defined by S&ID for power profile computation (Ref: S&ID letter 64 MA 3540).

Table 3-III shows the energy consumptions on a G&N activity and G&N equipment basis. The vertical column to the left indicates the various G&N activities (phases of operation). This column also indicates the power requirement and operating time for each specific activity. The top row indicates the power requirement and operating time of each G&N power-consuming equipment.

BLOCK II

COMMAND MODULE




Figure 3-1. Electrical Load on Primary +28 VDC Power Supply

BLOCK II
COMMAND MODULE

Table 3-III. Block II Command Module Power Profile for 14-Day Lunar Orbit Mission

		TOTAL	22, 577	7, 303	0, 518	2, 496	17.059	2, 469	1. 471	0,196	54, 089
		Ophica series		1, 658		0.936					2, 594
	•	O See See See See See See See See See Se		0, 503		0, 283		•		•	0,786
(Kilowatt Hours)	5	THOOL OI. 82.7			0.170	0.418	12,713	i	•	0,043	13. 344
CONSUMPTION (Kilow		Day of the control of	15,891	3.619	-	i		2, 307	0,847		22.664
ENERGY CONSUI	6	C. S.		i	:		4,346	0.162	İ		4. 508
MODULE		Paris Survey			-				0.624	0,153	0.777
II COMMAND	-	One Operate FOC of the Tronts	8.686	1, 523	0,348	0.859	ļ	!		-	9.416
SUMMARY OF BLOCK II		gen activity	Accomplish & confirm course corrections inactivity & Monitor 65,72 hrs.	Alignments Lendmark Trackings SXT Sightings 575, 5 watts 12.69 hrs.	Star Occultation Sightings 178, 5 watts 2, 90 hrs.	SXT Sightings (Midcourse) 348,8 watts 7.16 hrs.	Inactivity & Monitor 78.5 watts 217.31 hrs.	Inactivity & Monitor 305, 2 watts 8.09 hrs.	Computer Updates Major Maneuvers 495, 2 watts 2.97 hrs.	Computer Updates 268.5 watts 0.73 hrs.	TOTAL 308.30hours
		Operating Mode	<	æ	υ	Q	Þ	£.	5	×	

3-5 STATUS OF COMMAND MODULE AGC PROGRAMS

Table 3-IV lists current Command Module memory estimates and the status of AGC programs. The status of LEM AGC programs is not reported at this time.

A high and low word estimate is given with each program. Each status is defined as follows:

- (1) Planning stage
- (2) Programming stage
- (3) Checkout on AGC simulation
- (4) Checkout on G&N simulation
- (5) Checkout on AGC

Table 3-IV. Current Memory Estimates and the Status of Command Module AGC Programs

		· ·	Estimate rds)
Program	Status	High	Low
List Processing Interpreter	(5)	1712	1712
AGC Executive	(5)	253	253
AGC Waitlister	(5)	145	145
AGC System Exerciser	(5)*	500**	294**
G&N System Exerciser	(4)	650	400
Display, Keyboard, and		j	
Telemetry	(5)	2000*	2000*
Input/Output Control	(5)*	1750**	1275**
Midcourse & Orbital Navigation	(5)*	2000**	1500**
Midcourse & Orbital Guidance	(3)	500	500
Pre-Launch Platform Alignment	(5)	400**	350**
In-Flight Platform Alignment	(4)	1024	900
Re-Entry Control	(4)	1800	1200
Injection and De-Boost	(4)	1000	400
Restart	(5)*	500**	200**
Aim-Point Determination			
& Abort	(1)	4000	2000
Totals		18234*	13129*

^{*}These values have changed since the last report, Rev. 20.

DATE 6/15/64 PAGE 3-7

^{**}Programs in stage (5) whose low and high estimates are not identical reflect an anticipated increase in computational facility.



Section 4

LUNAR EXCURSION MODULE DATA

4-1 RELIABILITY

The numbers in table 4-I do not assume the use of in-flight spares or repair. The changes in reliability values result from changes in operating times which are based on MIT/IL's Guidance Monitor System Note No. 3, dated 23 January 1964.

Subsystem	Operating Time (hrs)	Probability of Mission Success
IMU	6.25*	0.99914*
AGC	6.25*	0.99797*
PSA	6.25*	0.99927*
CDU (5)	6.25*	0.99896*
OMU	0.75*	0.99997*
Total G&N S	ystem	0.9953*

Table 4-I. Reliability (as of 6/15/64)

4-2 WEIGHTS FOR LEM

Lunar Excursion Module weights are presented in table 4-II. In general the data conform to the information contained in paragraphs 2-1, 2-1.1, and 2-1.2.

The row labeled "Bare Guidance System" is inserted to provide for comparisons with similarly specified systems.

At NASA coordination meeting L6A, 26-27 May 1964, the installation configuration of the telescope and IMU was changed from the existing installation, wherein the IMU was inside the LEM pressure shell, to an outside configuration. Moreover, the vibration environment recently specified in preliminary ICD LIS-520-10001, dated 26 May 1964, "LEM Design Environment," states levels which are much greater than anticipated in the G&N design. Vibration isolation mounts for the telescope and IMU

^{*}These values have changed since last report (Rev. 20).



Table 4-II. Esti	Estimated Weichts of LEM G&N Components (lbs at 1 g)	hts of LEM	G&N Compo	ments (lbs s	t 1 gl	
	Status	***********	Status		Status	Design Load Wt.
Item	2/64 (a)	(b-a)	5 /64 (b)	(c-b)	6 /64 (c)	5/64 (d)
CDU's	15.0 (E)	+7.9	22.9(正)	0.0	22. 9 (E)	**
Telescope and All Eyepieces	24.5(E)	0.0	24. 5 (E)	0.0	24.5(E)	
Eye Register for Reticule	2.0(E)	0.0	2.0(E)	0.0	2.0(E)	
Two-Digit Readout for		-				
Reticule	5.0(E)	0.0	5.0(E)	0.0	5.0(E)	·-
IMU	42.0(E)	0.0	42.0(E)	0.0	42.0(E)	
AGC/PSA Interconnection						
Assy	10.0(E)	0.0	10.0(E)	0.0	10.0(E)	
AGC Display and Controls	19.5 (E)	0.0	19.5(E)	0.0	19.5(E)	
Other Display and Controls	15.0(E)	0.0	15.0(E)	0.0	15.0(E)	
Book of Procedures, etc	2.0(E)	0.0	2.0(E)	0.0	2.0(E)	
AGC	41.5 (E)	+2.5	44.0(E)	0.0	44.0(E)	
AGC Cover	4.3(E)	-2.0	2.3(E)	0.0	2.3(E)	,
PSA	24.8(E)	0.0	24.8(E)	0.0	24.8(E)	
PSA Cover	2.4(E)	0.0	2. 4 (E)	0.0	2. 4 (E)	
TOTAL	210.0*	+6.4	216. 4	0.0	216. 4	
	Control					
	Weight					
Bare Guidance System	6 00	4 G	9 01	•	110 x	
(IMU, For, and computer)	700.0) •	0 .011	• •		
* Control Weight specified in Le	ified in Letter PG-64-113 (March 6, 1964) from Mr. D. Gilbert,	113 (March	6, 1964) fr	om Mr. D.	Gilbert, ASPO,	ó.
æ	n assigned.	; ;				

DATE 6/15/64

PAGE 4-1

will be required. These changes will cause weight increases for the vibration isolation mounts, a longer telescope, and a navigation base separate from the basic LEM structure. An increase in the control weight will be requested. The weights shown in Table 4-II do not include the effect of these changes.

4-3 POWER REQUIREMENTS

The estimate for LEM power and energy consumption shown in figure 4-1 is based upon recent Command Module G&N Block II data and preliminary ICD LIS-390-2, LEM Electrical Load Analysis Form.

Table 4-III shows the energy requirements for each G&N activity on a power level basis. The table is also based upon LEM ICD LIS-390-2. The vertical column to the left indicates the various G&N activities (phases of operation). The column also indicates the power requirement and operating time for each specific activity. The top row indicates the power requirement and operating time of each G&N power consuming equipment. The table sums up the energy consumption for power consuming equipment.




Figure 4-1. Electrical Load on Primary +28 VDC Power Supply

Table 4-III. LEM Power Profile Based on LEM ICD LIS-390-3

	Summary of Lunar Excursion Module Energy Consumption in Kilowatt Hours	rgy Consumpt	ion in Kilowati	Hours	,				
		1	2	8		9	•	1	
Mode	LEM G&N Activity	37.40°0	AND TO SOLUTION OF	SARA CO.	AND THE POPULATION OF THE POPU	A PART I C.	AND OF STREET		Total
I	Inactivity 87, 40 hours 58, 5 watts	0, 000	l	•	•	5, 113	_	ı	5, 11.8
п	Inactivity Alignment Midcourse Measurements Il, 72 hours	l	1, 231		3, 484		0.298	Negligible	5.018
Ш	Guidance During Major Event 0,20 hours 427.7 watts	ł	0.021	l	0.059		0,005	I	0.000
ΛI	Inactivity 20.05 hours 68.5 watts		_	0,20	 	1, 178	ŀ	1	1. 37\$
۸	Inactivity 15.70 hours 68.5 watts	l	ŀ	0.157	.	0, 918	ı	Negligible	1. 075
	Total Hours	000.00	1, 252	0,357	3, 543	[.] 7, 204	0.303	Negligible	12, 659

Section 5

GLOSSARY AND SYSTEM DEFINITION

Apollo Guidance Computer (AGC)

<u>CM BLOCK I</u> A single complete flight computer containing all logic, memory, associated power supplies, and all interface circuits except those identified with the CDU's. Does not contain the associated displays and controls.

Consists of two trays containing replaceable electronic modules, the AGC end connector, and toe plate. Does not include the necessary cold plate or the G&N to S/C Interface Assembly which is located in the adjacent area. Space exists for carrying an extra spare pair of AGC trays. These would not function in this spares location but could interchange with faulty trays in the active position. The spare trays are reported separately.

CM BLOCK II Two complete and active computers each having the same functions as the Block I AGC. Consists of two wiring matrix headers mounted on each side of the cold plate. This cold plate is not included in this accounting and must be moved up from the Block I configuration location. The modules of the "X" computer mount on one of these headers, those of the "Y" computer on the other.

Block I and Block II AGC's are not interchangeable.

<u>LEM</u> A single complete flight computer having the same functions as one of the <u>Block</u> II computers. Unless installation constraints yet to be determined prevent it, the LEM computer will be physically identical with the Block II computers.

AGC Covers

CM BLOCK I Not required.

<u>CM BLOCK II</u> Two covers, one for each computer, may be required if it becomes necessary to seal the Malco connectors against moisture.

LEM Same as Block II except that there is only one cover.

DATE 6/15/64 PAGE 5-1

AGC Spares

CM BLOCK I Spare AGC logic and memory trays.

CM BLOCK II AND LEM No spares.

Alignment Optical Telescope (AOT)

CM BLOCK I AND BLOCK II Not in CM; see Optical Subsystem.

<u>LEM</u> A 3-position periscope with single-degree-of-freedom manually read reticule for alignment of the IMU.

Bellows Assembly

CM BLOCK I AND CM BLOCK II Flexible pressure seal between CM structure and optical subsystem on NAV BASE for penetration of pressure hull with optics.

<u>LEM</u> One bellows with a double convoluted wall and two seals providing a flexible seal for pressure penetration of the AOT in the spacecraft.

Book of Procedures

CM Not in CM; see MDV.

<u>LEM</u> Book or other form of maps, charts, procedures, instructions, etc., needed for lunar operations.

Coupling Data Unit (CDU) Assembly

The CDU provides the necessary signal interfaces among the IMU gimbal angles, optics gimbal angles, radar gimbal angles, angle registers in the AGC, the spacecraft autopilot attitude error signals, and the tracking radar command error signals.

<u>CM BLOCK I</u> Five interchangeable gear boxes each with necessary motor tachometer, resolver synchros, and encoder with mounting frame work. Does not include associated electronics which are located in the PSA.

CM BLOCK II Functionally identical to Block I except the instrumentation is all electronic. Includes all support electronics (including special power supply) and header and is located in same volume as Block I CDU's. Changes in resolver synchro characteristics and mode controls make Block I and II CDU's noninterchangeable.

LEM Interchangeable with CM Block II CDU's except for the headers.

Cold Plates

CM BLOCK I, BLOCK II, AND LEM Cold plates for the IMU are built into the IMU. Necessary cold plates for electronics are part of the equipment supplied by the spacecraft manufacturer.

Control Electronics Assembly

<u>CM BLOCK I</u> Consists of one power transformer, one relay and diode module, and a bracket end connector. Used to support display and control functions.

CM BLOCK II May be relocated with other similar functions.

LEM Not defined in LEM.

Coolant Hoses

CM BLOCK I AND CM BLOCK II Consists of (1) two aluminum flex coolant hoses, one between IMU and spacecraft and one between optics and spacecraft, (2) bracket assembly screws and clamp, and (3) entrapped coolant. Note that a third aluminum flex coolant hose between the optics and the IMU is considered as part of the weight of the optics base.

<u>LEM</u> Not identified as part of LEM.

Display and Control/Apollo Guidance Computer (D&C/AGC)

CM BLOCK I AND BLOCK II Number displays and keyboard control associated with the operation of the AGC. Two functionally identical and parallel operation units: one in lower equipment bay and one on main panel between left and center couches.

LEM Identical to CM except only a single unit is required.

D&C Electronics Assembly

CM BLOCK I Consists of a chassis, a relay and diode module, a demod. elect. module, a saturable reactor, a time delay module, a connector, and wiring. Used to support display and control functions.

CM BLOCK II Not defined at this time.

LEM Not defined in LEM at this time.

Eye Register for Reticule

CM Not in CM.

<u>LEM</u> Device or equipment not yet defined in detail, to position the **LEM** pilot's eye to use the window marking reticule pattern for landing point observation and selection during the constant flight path phase of landing.

Film Cartridges

CM BLOCK I AND BLOCK II Consists of film cartridges and film for map and data viewer.

LEM Does not exist in LEM.

G&N Indicator Control Panel

CM BLOCK I AND BLOCK II Consists primarily of controls and displays for the operation of the optics, MDV, IMU temperature control, panel brightness control, and attitude impulse control. It includes display and control elements, panel, panel wiring, and supporting hardware. Block II panel will probably contain horizon photometer controls also.

LEM Not defined at this time for LEM.

G&N Interconnection Assembly

CM BLOCK I Consists of PSA End Connector Assembly and interconnect wiring harness which electrically ties together the assemblies that constitute a completely integrated system. This term does not include the G&N to S/C Interface Assembly weight or the weights of harness support brackets which are an NAA responsibility.

DATE 6/15/64

CM BLOCK II Similar to Block I but not interchangeable with Block I.

<u>LEM</u> Not clearly defined but at present is called the AGC/PSA Interconnection Assy. Because of the wide separation of G&N components, most interconnection will be accomplished as part of spacecraft wiring.

G&N to S/C Interface Assembly

<u>CM BLOCK I</u> Interconnections between the spacecraft wiring channel, the computer end connector, and the PSA end connector. Contains no active electronics. The G&N Harness Tray Assy is also included as part of this assembly.

<u>CM BLOCK II</u> Similar in function to Block I except the configuration is much different and not interchangeable with Block I.

LEM Not identified yet as a separate item in LEM.

Horizon Photometer

<u>CM BLOCK I</u> Only 100 Series Systems will have a horizon photometer and star tracker, using a Block II optical sextant. Zero-series Block I weights do not include an horizon photometer.

<u>CM BLOCK II</u> An earth horizon brightness photometer and automatic star tracker for navigation measurements against the earth's illuminated limb. The sensors are incorporated into the head of the SXT, the weight of which includes this function. The PSA includes support electronics.

LEM Not part of LEM.

Inertial Measurement Unit (IMU)

<u>CM BLOCK I</u> Size 14 IMU (14-inch case diameter) gimbal assembly including all parts inside hermetic case and including entrapped coolant.

CM BLOCK II Size 12.5 IMU functionally interchangeable with Block I unit, but not physically interchangeable with Block I.

LEM Size 12.5 IMU as described above.

IMU Control Panel

CM BLOCK I Consists of panel, wiring, attitude error meter, CDU transfer switch, manual alignment switch, CDU mode control switches, connector, and supporting hardware.

<u>CM BLOCK II</u> Does not exist in Block II. Moding is done by AGC program and AGC push buttons.

LEM Not defined at this time for LEM.

Long-Eye-Relief Eyepieces

CM BLOCK I AND BLOCK II Consists of a SXT and a SCT eyepiece to provide eye relief of at least 1.6 inches for closed-visor operation. Used in place of normal eyepieces of SXT and SCT.

<u>LEM</u> Long-eye-relief eyepieces for the AOT are included as part of the AOT in this accounting.

Map and Data Viewer (MDV)

CM BLOCK I AND BLOCK II Film viewer for display of maps, charts, procedures, etc. Weight includes one film cartridge for Block I MDV and tentatively two for Block II MDV.

LEM Not in LEM; see Book of Procedures.

NVB and Resilient Mounts

<u>CM BLOCK I</u> Rigid beryllium structure supporting the IMU and the optical subsystem with its associated hardware. The NVB is attached to the spacecraft using flexible resilient mounts to prevent spacecraft strains from distorting the NVB and the alignment between the IMU and Optics. These mounts also provide shock and vibration attenuation.

CM BLOCK II Functionally similar to Block I but will be lighter and provide for mounting the size 12.5 IMU.

<u>LEM</u> The need for tieing the AOT and IMU together exists but is accomplished by using structure provided by the spacecraft contractor. See paragraph 4-2.

Optical Eyepieces

CM BLOCK I AND BLOCK II Removable SXT eyepiece and SCT eyepiece.

LEM Included as part of the AOT.

Optical Subsystem

CM BLOCK I Consists of SXT, SCT, Optical Base, and associated hardware defined as follows:

SXT: Sextant -- a two-line-of-sight, narrow-field, two-

degree-of-freedom sextant and its attached gearing.

SCT: Scanning Telescope -- a single-line-of-sight, wide-

field-of-view, two-degree-of-freedom articulation

optical instrument and its attached gearing.

OPTICAL BASE: Base for SXT and SCT with associated gearing and

internal cooling. Includes the weight of the coolant

hose between the IMU and Optical Base.

<u>CM BLOCK II</u> Similar to Block I except for changes in the sextant to provide line-of-sight velocity control directly without CDU's. The horizon photometer and automatic star tracker are incorporated into the SXT.

LEM Not in LEM; see AOT.

Optical Shroud & Cover Assembly

CM BLOCK I AND BLOCK II Consists of the optical shroud and protective cover.

LEM Does not exist in LEM.

Power Servo Assembly (PSA)

CM BLOCK I Consists of most of the support electronics: power supplies; IMU, Optics, and CDU servos; IMU temperature control; accelerometer and gyro pulse torquing; and signal conditioning electronics. Consists of 10 trays with replaceable modules which plug into the PSA end connector assembly. Includes front toe plate but not the cold plate.

<u>CM BLOCK II</u> Similar in function to Block I but does not contain the CDU servos and signal conditioning electronics needed in Block I. Includes electronics for horizon photometer and automatic star tracker. Consists of a single plane matrix header to mount onto the cold plate with the modules plugging onto the top.

DATE 6/15/64 PAGE 5-7

<u>LEM</u> Consists of electronics similar to those identified in the Block II PSA minus various electronics modules. Does not include CDU, Optics, and Photometry electronics associated with the Block II PSA.

PSA End Connector Assembly

<u>CM BLOCK I</u> Electrical interconnection between the PSA trays, the G&N Interconnection Assy, and the G&N to S/C Interface Assy. The End Connector weight is reported in the G&N Interconnection Assembly weight.

CM BLOCK II Not identified as a separate item; will be part of the PSA matrix header.

LEM Not yet defined. Will probably not exist in LEM.

PSA Covers

CM BLOCK I Not required.

CM BLOCK II Cover to protect the PSA module connections from moisture during flight.

LEM Same as Block II except lighter in weight.

Signal Conditioner Assembly

CM BLOCK I Conditions signals for telemetry.

CM BLOCK II AND LEM Not used.

Two-Digit Readout for Reticule

CM Not in CM.

<u>LEM</u> A 2-digit readout driven by the AGC from 00 to 99 to indicate range component of landing point using fixed numbered scale on window reticule.