




*m* - *Bellcom IV*  
*fm file* *Mummert*  
OCT 2 1 1969

NATIONAL AERONAUTICS AND SPACE ADMINISTRATION

MSC INTERNAL NOTE NO. 68-FM-256

October 11, 1968

68-FM-256  
VERIFICATION OF SUNDISK ORBITAL  
NAVIGATION PROGRAM




Technical Library, McDonnell, Inc.

NOV 3 1969

Mathematical Physics Branch

MISSION PLANNING AND ANALYSIS DIVISION

MANNED SPACECRAFT CENTER  
HOUSTON, TEXAS



(NASA-TM-X-69716) VERIFICATION OF SUNDISK  
ORBITAL NAVIGATION PROGRAM (NASA) 112 p

N74-70626

Unclassified  
00/99 16149

MSC INTERNAL NOTE NO. 68-FM-256

---

PROJECT APOLLO

VERIFICATION OF SUNDISK ORBITAL NAVIGATION PROGRAM

By Richard E. Eckelkamp  
Mathematical Physics Branch

---


October 11, 1968

MISSION PLANNING AND ANALYSIS DIVISION  
NATIONAL AERONAUTICS AND SPACE ADMINISTRATION  
MANNED SPACECRAFT CENTER  
HOUSTON, TEXAS

Approved:

  
James C. McPherson, Chief  
Mathematical Physics Branch

Approved:

  
John P. Mayer, Chief  
Mission Planning and Analysis Division

## CONTENTS

| Section   | Page |
|---|------|
| SUMMARY . . . . .   | 1    |
| INTRODUCTION . . . . .  | 1    |
| The Kalman-Schmidt Filter . . . . .   | 2    |
| SUMMATION OF ORBITAL NAVIGATION EQUATIONS . . . . .                               | 3    |
| Coordinate Systems. . . . .   | 3    |
| Orbital Integration . . . . .   | 4    |
| Use of Landmark Sightings in the Kalman-Schmidt Filter. . . . .                   | 6    |
| The b-vector. . . . .   | 7    |
| The W matrix and $\alpha^2$ . . . . .   | 9    |
| The observation residual. . . . .   | 11   |
| The CMC's Implementation of the Kalman Filter . . . . .                           | 12   |
| Verification of the Kalman factor . . . . .                                       | 13   |
| Verification of the W updating equation . . . . .                                 | 14   |
| Unknown landmarks . . . . .   | 17   |
| THE CMC CODING. . . . .   | 20   |
| Results of Coding Review. . . . .   | 37   |
| Flow chart comparison . . . . .   | 37   |
| Comparison of equation and astronaut procedure to coding. . . . .                 | 37   |
| Illegal interfaces. . . . .   | 37   |
| ASTRONAUT PROCEDURES. . . . .   | 37   |
| BIT-BY-BIT TESTING. . . . .   | 37   |
| CONCLUSION. . . . .   | 38   |
| APPENDIX A - MIT FLOWCHARTS FOR SUNDISK REV 212 P22 . . . . .                     | 39   |
| APPENDIX B - MIT APOLLO COMPUTER LOGIC CHECKLIST INTERFACE<br>(GSOP IV) . . . . . | 61   |

| Section   | Page |
|---|------|
| APPENDIX C - APOLLO 7 CREW CHECKLIST FOR P22. . . . .                                       | 79   |
| APPENDIX D - SUNDISK P22 VERIFICATION TEST - TWO KNOWN LAND-MARKS CASE. . . . .             | 85   |
| APPENDIX E - SUNDISK P22 VERIFICATION TEST - ONE KNOWN, ONE UNKNOWN LANDMARK CASE . . . . . | 97   |
| REFERENCES. . . . .   | 107  |

## TABLES

| Table  |  | Page |
|--------|--|------|
| D-I    | DIFFERENCE BETWEEN THE BIT-BY-BIT AND THE<br>ENGINEERING-SIMULATION UNIT b-VECTOR. . . . .   | 87   |
| D-II   | THE BIT-BY-BIT UNIT b-VECTOR . . . . .   | 88   |
| D-III  | THE BIT-BY-BIT VECTOR UPDATES. . . . .   | 89   |
| D-IV   | ENGINEERING-SIMULATION VECTOR UPDATES. . . . .   | 90   |
| D-V    | BIT-BY-BIT ESTIMATED LANDMARK POSITION . . . . .   | 91   |
| D-VI   | ENGINEERING-SIMULATION ESTIMATED LANDMARK POSITION . .   | 92   |
| D-VII  | DIFFERENCE BETWEEN THE BIT-BY-BIT AND THE<br>ENGINEERING-SIMULATION W-MATRIX AFTER THE SECOND<br>INCORPORATION . . . . .                         | 93   |
| D-VIII | DIFFERENCE BETWEEN THE BIT-BY-BIT AND THE<br>ENGINEERING-SIMULATION W-MATRIX AFTER MARK 5, SECOND<br>INCORPORATION . . . . .                     | 94   |
| D-IX   | BIT BY BIT W MATRIX AFTER MARK 5, SECOND<br>INCORPORATION . . . . .  | 95   |
| E-I    | BIT-BY-BIT VECTOR UPDATES. . . . .   | 99   |
| E-II   | ENGINEERING-SIMULATION VECTOR UPDATES. . . . .   | 100  |
| E-III  | BIT-BY-BIT ESTIMATED LANDMARK POSITION . . . . .   | 101  |
| E-IV   | ENGINEERING-SIMULATION ESTIMATED LANDMARK POSITION . .   | 102  |
| E-V    | DIFFERENCE BETWEEN THE BIT-BY-BIT AND THE ENGINEERING-<br>SIMULATION ESTIMATED POSITION AND VELOCITY VECTOR . .                                  | 103  |
| E-VI   | DIFFERENCE IN THE RESIDUALS (ACTUAL MINUS ESTIMATED)<br>OF THE BIT-BY-BIT AND THE ENGINEERING-SIMULATED<br>POSITION AND VELOCITY VECTOR. . . . . | 104  |
| E-VII  | DIFFERENCE IN THE DIAGONAL OF THE BIT-BY-BIT AND THE<br>ENGINEERING-SIMULATION W-MATRIX . . . . .  | 105  |
| E-VIII | DIAGONAL VALUES AT SPECIFIED POINTS IN THE<br>BIT-BY-BIT W-MATRIX . . . . .  | 106  |

## VERIFICATION OF SUNDISK ORBITAL NAVIGATION PROGRAM

By Richard E. Eckelkamp

### SUMMARY

This paper presents a detailed explanation and test verification of SUNDISK 282 orbital navigation program 22 (P22). Included are a step-by-step analysis of the coding and flow charts, a summary of the equations utilized, an outline of astronaut procedures, and charted results of bit-by-bit test cases.

### INTRODUCTION

Orbital navigation, as contained in the roped version 282 of SUNDISK for the command module computer (CMC), will be exercised for the first time on Apollo 7. This report fulfills a need of gathering and interpreting the official documentation concerning the program under one cover.

In orbital navigation, optical sightings on landmarks are statistically weighed to correct the vehicle position and velocity in the CMC as well as the position of the landmarks. This process can thus determine both the orbit and the landing site.

The explanation of P22 will begin with a summation of the formulation found in parts 5.1 to 5.2.8 of Section V of the GSOP (ref. 1). A line-by-line interpretation of the coding, as presented in reference 2, will then be given. The MIT flow charts are available to aid in the understanding of the coding. A resume of astronaut procedures and the test results follows.

### The Kalman-Schmidt Filter

Accurate estimates of the state vectors of bodies relative to particular reference systems may be computed by integration of the equations of state complemented with processing of navigational observations. One method of processing observations, the Kalman-Schmidt filter, adapted from filter theory in electrical engineering, statistically weighs single observations and uses them to correct state vectors while smoothing observational noise.

In orbital navigation the state vector consists of the command module's position and velocity and the position of a given landmark in an inertial coordinate system. Telescope or sextant observations of the landmark relative to an inertial platform constitute the measurement.

Before presenting detailed information of the navigation processes, a brief outline of the Kalman-Schmidt method is useful.

To correct the state at time  $t_i$

- Make an observation  $Q_i$  at  $t_i$
- Integrate the state vectors as stored in the vehicle computer

to  $t_i$

$$\int_{i-1} \begin{bmatrix} \underline{r}_c \\ \underline{v}_c \\ \underline{r}_l \end{bmatrix} = \begin{bmatrix} \underline{r}_c \\ \underline{v}_c \\ \underline{r}_l \end{bmatrix}_i$$

where

$\underline{r}_c$  = position vector of command module

$\underline{v}_c$  = velocity vector of command module

$\underline{r}_l$  = position vector of landmark

- Compute from this state vector the estimated observation  $\hat{Q}_i$

d) Find the observation residual  $Q_i - \hat{Q}_i = \delta Q_i$

e) Compute the weighting factor  $\underline{\omega}_i$  for the residual at  $t_i$

This factor is obtained by propagating the square root of the state covariance matrix (or matrix of state uncertainty) to  $t_i$ .

f) Correct the state

$$\begin{bmatrix} r_c \\ v_c \\ r_\ell \end{bmatrix}_i^+ = \begin{bmatrix} r_c \\ v_c \\ r_\ell \end{bmatrix}_i + \underline{\omega}_i \delta Q_i$$

g) Also correct, or update,  $\underline{\omega}_i$  to  $\underline{\omega}_i^+$ , where the plus denotes the updated quantity.

This statistically weighting of single observations for vector correction works well and is equivalent to the modified weighted least square (WLS) method used for ground-based navigation. Generally, the number of observations required to reduce initial errors to within the system noise level and maintain this level of accuracy varies with mission phase and navigation requirements.

#### SUMMATION OF ORBITAL NAVIGATION EQUATIONS

##### Coordinate Systems

To locate any body at a given time a coordinate system is necessary. For the Apollo program, the basic reference system is the nearest Besselian year (NBY) coordinate system.

The NBY system is defined in an earth-centered inertial Cartesian system. The X-axis is along the line of intersection of the mean equatorial plane and the mean orbit plane of the earth (equinox); Z is along the mean north pole; and Y completes the right-handed triad - all defined at the time of the beginning of the NBY. Vectors dated after the Julian date of June 30 are referenced to the following year. For example, the Besselian year 1968 begins on Julian day January 1.283, 1968; the Besselian year 1969, January 0.525, 1969. The center of this system is translated to the moon's center when the vehicle is in lunar reference.

As stated in reference 3, the CMC programs, including orbital navigation, utilize an approximate system to locate earth fixed targets. The transformation from this system to the NBY system for a state vector  $\tilde{r}_\ell$  in this CMC system is

$$\tilde{r}_{\ell \text{NBY}} = \begin{bmatrix} 1 & 0 & -A_y \\ 0 & 1 & A_x \\ A_y & -A_x & 1 \end{bmatrix} \begin{bmatrix} \cos A_z & -\sin A_z & 0 \\ \sin A_z & \cos A_z & 0 \\ 0 & 0 & 1 \end{bmatrix} \tilde{r}_\ell$$

where  $\tilde{r}_\ell$  and  $\tilde{r}_{\ell \text{NBY}}$  are column vectors. The onboard state vector  $\tilde{r}_\ell$  is first rotated about the true Z-axis by an angle  $-A_z$  where

$$A_z = A_{z0} + \omega(t + t_{\text{ephem}})$$

$A_{z0}$  = angle between the X-axis and the Greenwich meridian at midnight just prior to the year preceding the reference Besselian year

$t_{\text{ephem}}$  = elapsed time between July 1 and the time that the CMC clock was zeroed

$t$  = time indicated in the CMC clock

$\omega$  = sidereal rotation rate of the earth

The transformation is completed by making small angular rotations about the X- and Y- axes. The values of  $A_x$  and  $A_y$  are constant for a given mission. These introduce an approximation. The resulting errors are proportional to the elapsed time between  $t$  and the time associated with the evaluation of  $A_x$  and  $A_y$ .

#### Orbital Integration

The state vector for the CSM is periodically integrated using either the conic or the Encke method. In the conic mode, the perturbing acceleration,  $\tilde{a}_d(t)$ , in the basic equation

$$\frac{d^2}{dt^2} \underline{r}(t) + \frac{\mu_e}{r^3} \underline{r}(t) = \underline{a}_d(t)$$

is omitted. In the precision mode, an oscillating conic is defined at  $t_o$ , again ignoring  $\underline{a}_d(t_o)$ . The perturbing acceleration is then integrated separately for any  $t_o + \Delta t$  using Nystrom's method. When the perturbed portion of the vector reaches a certain magnitude, currently defined as 8 kilometers, a new conic is defined, a procedure called rectification. The time of the new conic,  $t_o'$ , is

$t_o' = t_o + n\Delta t$ , where  $n\Delta t$  is the elapsed time since the last rectifications at  $t_o$ .

The square root of the state covariance matrix,  $W$ , is also propagated forward. The covariance, or correlation matrix, is defined for orbital navigation as

$$E(t) = \begin{bmatrix} \underline{\varepsilon} & \underline{\varepsilon}^T & \underline{\varepsilon} \underline{\beta}^T \\ \underline{n} & \underline{\varepsilon}^T & \underline{n} \underline{\beta}^T \\ \underline{\beta} & \underline{\varepsilon}^T & \underline{\beta} \underline{\beta}^T \end{bmatrix} 9 \times 9$$

where  $\underline{\varepsilon}$ ,  $\underline{n}$ , and  $\underline{\beta}$  are partial estimates of the errors in CSM position, CSM velocity, and landmark positive, respectively. The  $W$  matrix is defined by

$$E(t) = W(t)W(t)^T$$

( $T$  denotes transpose) and extrapolated by numerical integration of

$$\frac{d}{dt} W(t) = \begin{bmatrix} 0 & I & 0 \\ G(t) & 0 & 0 \\ 0 & 0 & 0 \end{bmatrix} W(t) \quad 9 \times 9$$

where

$$G(t) = \frac{\mu_e}{r^5(t)} [3\dot{r}(t)\dot{r}(t)^T - \dot{r}^2(t)I]_{3 \times 3}$$

$I = 3 \times 3$  identity matrix

$O = 3 \times 3$  zero matrix

Despite the use of rectification, initial errors in the state and dynamic biases neglected in the equations, for example, drag, eventually cause the CMC vector to diverge from the actual vector. The W matrix is subsequently affected the same. Navigation measurements are utilized to correct both the state and the W matrix. In orbital navigation landmark sightings are processed through the Kalman-Schmidt filter for this purpose.

#### Use of Landmark Sightings in the Kalman-Schmidt Filter




Figure 1.

Given that a mark relative to the navigational base coordinate system has been made on a landmark and transmitted to the CMC, program 22 will utilize this data to correct the state vector.

As outlined in the introduction, an observation is computed for the same time as the observed data. The difference between the actual and computed observation,  $\delta Q_i$ , is weighted with  $\omega_i$  and added to the state vector.

The b-vector. - In the computation of  $\underline{\omega}_i$ , where

$$\underline{\omega}^T = \frac{1}{z^2 + \alpha^2} \cdot \underline{z}^T \underline{w}^T \quad (1)$$

$$\underline{z} = \underline{w}^T \underline{b}$$

the b-vector, defined as

$$\underline{b} = \frac{\partial (\text{COMPUTED OBSERVATION})}{\partial (\text{COMPUTED STATE})} = \frac{\partial Q_i}{\partial X_i} \quad (2)$$

indicates how much and in which direction the state will change for a given change in the observation. Referring to figure 1 and following the derivation from reference 3, let  $\underline{u}_s$  be a unit vector pointing toward an imaginary star.

$$\text{Assume } \underline{u}_s \times \underline{r}_{cl} \neq 0.$$

To get the  $\underline{b}$  vector, take the dot product

$$\underline{r}_{cl} \cos \theta = \underline{r}_{cl} \cdot \underline{u}_s$$

Take the differential:

$$\delta \underline{r}_{cl} \cos \theta - \underline{r}_{cl} \sin \theta d\theta = \delta \underline{r}_{cl} \cdot \underline{u}_s \quad (3)$$

Now,

$$\underline{r}_{cl} = [\underline{r}_{cl} \cdot \underline{r}_{cl}]^{1/2}$$

$$\delta \underline{r}_{cl} = 1/2 [\underline{r}_{cl} \cdot \underline{r}_{cl}]^{-1/2} [\delta \underline{r}_{cl} \cdot \underline{r}_{cl} + \underline{r}_{cl} \cdot \underline{r}_{cl}]$$

$$\delta \underline{r}_{cl} = \frac{\underline{r}_{cl} \cdot \sigma \underline{r}_{cl}}{r_{cl}} \quad (4)$$

Substituting (4) into (3) and rearranging,

$$\frac{\underline{r}_{cl} \cdot \delta \underline{r}_{cl}}{r_{cl}} \cos \theta - r_{cl} \sin \theta d\theta = \delta \underline{r}_{cl} \cdot \underline{u}_s$$

$$\delta \theta = \left[ \frac{\underline{r}_{cl} \cos \theta}{r_{cl}} - \frac{\underline{u}_s}{r_{cl}} \right] \frac{1}{\underline{r}_{cl} \sin \theta} \cdot \delta \underline{r}_{cl}$$

Now if we choose  $\underline{u}_s$  perpendicular to  $\underline{r}_{cl}$

$$\delta \theta = - \frac{\underline{u}_s}{r_{cl}} \cdot \delta \underline{r}_{cl}$$

This is the relation which defines  $b$  for updating the relative position  $\underline{r}_{cl}$ . Since the CMC updates  $\underline{r}_c$  and  $\underline{r}_l$ , note

$$\underline{r}_c + \underline{r}_{cl} = \underline{r}_l$$

$$\delta \underline{r}_c + \delta \underline{r}_{cl} = \delta \underline{r}_l$$

Then (3) becomes

$$\delta \theta = \frac{-\underline{u}_s}{r_{cl}} \cdot [\delta \underline{r}_l - \delta \underline{r}_c]$$

$$= \frac{\underline{u}_s}{r_{cl}} \cdot [\delta \underline{r}_c - \delta \underline{r}_l]$$

The  $b$  - vector can be written compactly as

$$\underline{b} = \frac{1}{r_{cl}} \begin{bmatrix} \underline{u}_s \\ 0 \\ -\underline{u}_s \end{bmatrix}$$

Each observation point is incorporated twice, since two degrees of freedom are available perpendicular to  $\underline{r}_{cl}$ . For the first direction of correction,

$$\underline{u}_s^{(1)} = \text{unit } \left\{ \underline{r}_{cl} \times \left[ \underline{r}_{cl} \times \begin{pmatrix} 0 \\ 0 \\ 1 \end{pmatrix} \right] \right\}$$

In case the computer computation is difficult resulting from  $\underline{r}_{cl}$  being parallel or near-parallel to  $\begin{bmatrix} 0 \\ 0 \\ 1 \end{bmatrix}$ , use

$$\underline{u}_s^{(1)} = \text{unit } \left\{ \underline{r}_{cl} \times \left[ \underline{r}_{cl} \times \begin{pmatrix} 0 \\ 1 \\ 0 \end{pmatrix} \right] \right\}$$

For the second correction use  $\underline{u}_s^{(2)} = \text{unit} \left[ \underline{r}_{cl} \times \underline{u}_s^{(1)} \right]$ ,

where the plus indicates that  $\underline{r}_{cl}$  has been updated by the first correction.

The W matrix and  $\alpha^2$ . - The 9-by-9 W matrix in equation (1) represents a numerical estimate of the uncertainties associated with the mathematical description space. These uncertainties include noises and bias on the state vector and prediction models (lack of drag, for example) and limitations of their representation for programming. For convenience, the W matrix may be divided into nine 3-by-3 matrices:

$$W = \begin{bmatrix} w_0 & w_1 & w_2 \\ w_3 & w_4 & w_5 \\ w_6 & w_7 & w_8 \end{bmatrix} \quad (6)$$

At the beginning of a navigational sequence, this matrix must be set to an initial value representing, among other things, an estimate of state uncertainty. Each 3-by-3 matrix is taken initially to be a diagonal, since the initial self-correlations of vehicle position, vehicle velocity, and landmark position,  $w_0, w_4, w_8$  respectively, cannot be accurately determined a priori.

Further, the initial correlation between  $w_0$ ,  $w_4$ , and  $w_8$  are simplified. The correlation between  $w_0$  and  $w_4$  represented by  $w_1$  and  $w_3$ , are taken to be zero. For a known landmark, correlations between  $w_8$ ,  $w_0$ , and  $w_4$  are also taken to be zero.

For an unknown landmark (unl), however,

$$w_6 = K_0 w_0$$

$$w_7 = K_1 w_1$$

$w_8 = w_{\text{unl}} I + K_2 w_0$ , where  $K_0$ ,  $K_1$ ,  $K_2$ , and  $w_{\text{unl}}$  are constants.

These artificial correlations attempt to reflect the fact that the initial value of the unknown landmarks position will be heavily affected by errors in the vehicle state. In practice,  $K_0$  and  $K_1$  are set to zero in SUNDISK. For the program COLOSSUS a more realistic approach exists for the definition of errors associated with unknown landmarks.

As a marking sequencing continues, the numerical size and characteristics of the W matrix change. Correlations between the various elements grow. After each state vector update from mark data, the W matrix is also updated. The W matrix is extrapolated in time by integration, as outlined in the introduction.

The term  $\bar{\alpha}^2$  in equation (1) is a constant representing the uncertainties of the observational space. Noises and biases of the observing instruments and the observer are included.

It should be emphasized that since the filter employed in orbital navigation is nonoptimal, i.e., all known dynamic forces and data errors are not modeled, and the numerical values of  $\bar{\alpha}^2$  and the W matrix do not reflect the actual estimates of instrument and state vector error. Further, since the filter is linear, the relative value of W and  $\bar{\alpha}^2$  is the principle factor affecting the operation of the filter. For example, the filter will operate identically if values of  $w_0$  and  $\bar{\alpha}_0^2$  or  $k w_0$  and  $k^2 \bar{\alpha}^2$  are utilized, where k is any constant within the numerical limits of the computer.

The observation residual. - Recall from the introduction the equation for correcting the state vector:

$$\begin{bmatrix} \underline{r}_c \\ \underline{v}_c \\ \underline{r}_\ell \end{bmatrix}_i + = \begin{bmatrix} \underline{r}_c \\ \underline{v}_c \\ \underline{r}_\ell \end{bmatrix}_i + \omega_i \delta Q_i \quad (7)$$

One must compute  $\delta Q_i$ :

$$\delta Q = Q_i - \hat{Q}_i$$

Let  $\underline{u}_m$  be a unit vector in the NBY coordinate system pointing along the measured line of sight. Since the optical measurement occurs in the navigation base coordinate system, the transformation to NBY coordinates is

$$\underline{u}_m^{\text{NBY}} = [\text{REFSMMAT}]^T [\text{GIMBLE}] [\text{NAVGMBL}] \underline{u}_m^{\text{NBS}}$$

where the matrix [REFSMMAT] transforms from NBY to IMU coordinates, [GIMBLE], from body to IMU coordinates, and [NAVGMBL], from navigation base to body coordinates. Superscript T denotes a transpose.

For the actual observation,

$$\underline{u}_s \cdot \underline{u}_m = \cos \theta$$

$$\cos^{-1} (\underline{u}_s \cdot \underline{u}_m) = \theta_{\text{ACTUAL.}}$$

For the computed observation

$$\cos^{-1} (\underline{u}_s \cdot \underline{u}'_m) = \theta_{\text{COMPUTED}}, \text{ where the prime denotes a computed unit vector.}$$

Now

$$\delta Q = \theta_{\text{ACTUAL}} - \theta_{\text{COMPUTED}} = \cos^{-1}(\underline{u}_s \cdot \underline{u}_m) - \cos^{-1}(\underline{u}_s \cdot \underline{u}'_m)$$

$\delta Q = \cos^{-1}(\underline{u}_s \cdot \underline{u}_m) - \frac{\pi}{2}$ , since  $\underline{u}_s$  is perpendicular to the estimated line of sight,  $\underline{u}'_m$ .

#### The CMC's Implementation of the Kalman Filter

To utilize equation (7), up to five marks are made with the telescope or sextant on a particular landmark. A CMC routine, auto-optics, can aid the astronaut by aiming the observing instrument at the estimated landmark position. (The accuracy of the aim is proportional to the accuracy of the CMC state vector.) A residual,  $\delta Q$ , is computed with equation (8) and the  $b$  vectors are computed.

For computational purposes the  $W$  matrix is divided into 27 column vectors within the CMC. For example,  $W_0$  in equation (6) may be written

$$W_0 = \begin{bmatrix} w_0^T \\ w_1^T \\ w_2^T \end{bmatrix}$$

The nine dimensional quantities  $\underline{b}$ ,  $\underline{\omega}$ , and  $\underline{z}$  are also divided as

$$\underline{b} = \begin{bmatrix} b_0 \\ b_1 \\ b_2 \end{bmatrix} \quad \underline{\omega} = \begin{bmatrix} \omega_0 \\ \omega_1 \\ \omega_2 \end{bmatrix} \quad \underline{z} = \begin{bmatrix} z_0 \\ z_1 \\ z_2 \end{bmatrix}$$

The Kalman computations are then performed as

$$\underline{z}_i = \sum_{j=0}^2 W_{i+3j} \underline{b}_j, \quad i = 0, 1, 2 \quad (8)$$

$$\underline{\omega}_i^T = \beta \sum_{j=0}^2 \underline{z}_j^T W_{3i+j} \quad (9)$$

where

$$\beta = \frac{1}{\left( \sum_{j=0}^2 \underline{z}_j \cdot \underline{z}_j + \bar{\alpha}^2 \right)}$$

$$\delta \underline{x}_i = \delta Q \underline{\omega}_i, \text{ where } \begin{bmatrix} \delta \underline{x}_0 \\ \delta \underline{x}_1 \\ \delta \underline{x}_2 \end{bmatrix} = \begin{bmatrix} \delta \underline{r}_c \\ \delta \underline{v}_c \\ \delta \underline{r}_l \end{bmatrix} \quad (10)$$

Verification of the Kalman factor. - To verify that  $\underline{\omega}_i$ , defined in equation (9), is the Kalman weighting factor, which is normally defined as

$$\underline{\omega} = \underline{E} \underline{M}^T \left( \underline{M} \underline{E} \underline{M}^T + \bar{\alpha}^2 \right)^{-1} \quad (11)$$

begin with the compact definition given in reference 1, as

$$\underline{\omega} = \frac{1}{\underline{z}^2 + \bar{\alpha}^2} \underline{z}^T W^T$$

which implies

$$\underline{\omega} = \frac{1}{\underline{z}^2 + \bar{\alpha}^2} W \underline{z} \quad (12)$$

To get (12) expand the Kalman equation (11) using MIT terminology

$$\begin{aligned} \underline{\omega} &= \underline{W} \underline{W}^T \underline{M}^T \left( \underline{M} \underline{W} \underline{W}^T \underline{M}^T + \bar{\alpha}^2 \right)^{-1} \\ \underline{\omega} &= \underline{W} \underline{W}^T \underline{b}^T \left( \underline{b} \underline{W} \underline{W}^T \underline{b}^T + \bar{\alpha}^2 \right)^{-1} \end{aligned} \quad (13)$$

From reference (1),

$$\underline{z} = \underline{W}^T \underline{b}$$

Since the basic Kalman filter in (11) considers  $\underline{b}$  as a row vector,

$$\underline{z} = \underline{W}^T \underline{b}^T \quad (14)$$

Substituting (14) in (13)

$$\underline{\omega} = \underline{W} \underline{z} (\underline{z} \underline{z}^T + \alpha^2)^{-1}$$

which is MIT's formulation (12)

$$\underline{\omega} = \frac{1}{\underline{z}^2 + \alpha^2} \underline{W} \underline{z}$$

Verification of the W updating equation. - As noted in the introduction, the W matrix is updated after each incorporation of mark data. In CMC notation the update is

$$\begin{aligned} i &= 0, 1, \dots, 8 \\ \underline{w}_{i+9j} &= \underline{w}_{i+9j} - \gamma z_i \underline{\omega}_j \quad j = 0, 1, 2 \\ \gamma &= \frac{1}{1 + \sqrt{\beta \alpha^2}} \end{aligned} \quad (15)$$

To verify that equation (15) follows from Kalman theory, proceed as follows:

First equation (15) may be written (ref. 1) as

$$\underline{W}^+ = \underline{W} - \frac{\underline{\omega} \underline{z}}{1 + \sqrt{\frac{\alpha^2}{\underline{z}^2 + \alpha^2}}} \quad (16)$$

The Kalman update is defined as

$$\underline{E}^+ = (\underline{I} - \underline{\omega} \underline{M}) \underline{E}$$

Expanding in MIT notation,

$$\begin{aligned} (\underline{W} \underline{W}^T)^+ &= \underline{W} \underline{W}^T - \underline{\omega} \underline{b} \underline{W} \underline{W}^T \\ &= \underline{W} \underline{W}^T - \underline{W} \underline{W}^T \underline{b}^T (\underline{b} \underline{W} \underline{W}^T \underline{b}^T + \alpha^2)^{-1} \underline{b} \underline{W} \underline{W}^T \end{aligned}$$

Now following the derivation in reference 4,

$$(WW^T)^+ = W[I - \underline{z}(z^2 + \bar{\alpha}^2)^{-1}\underline{z}^T]W^T \quad (17)$$

In order for equation (17) to be valid, the right side of the equation must consist of some quantity times its transpose to update  $W$ . Otherwise, only  $E$  could be updated and the CMC  $W$  scheme would be invalid. Assume this quantity to be of the form

$$W[I - \beta \underline{z}\underline{z}^T] \quad (18)$$

where  $\beta$  must be found.

Equating equation (17) to equation (18) times the transpose of equation (18):

$$\begin{aligned} W[I - \underline{z}(z^2 + \bar{\alpha}^2)^{-1}\underline{z}^T]W^T &= W[I - \beta \underline{z}\underline{z}^T][I - \beta \underline{z}\underline{z}^T]^T W^T \\ I - \underline{z}\underline{z}^T(z^2 + \bar{\alpha}^2)^{-1} &= I - 2\beta \underline{z}\underline{z}^T + \beta^2 \underline{z}\underline{z}^T \underline{z}\underline{z}^T \\ \beta^2 z^2 - 2\beta + (z^2 + \bar{\alpha}^2)^{-1} &= 0 \end{aligned}$$

Using the quadratic formula

$$\begin{aligned} \beta &= \frac{2 \pm \sqrt{4 - 4z^2(z^2 + \bar{\alpha}^2)^{-1}}}{2z^2} \\ &= \frac{1 \pm \sqrt{1 - z^2(z^2 + \bar{\alpha}^2)^{-1}}}{z^2} \end{aligned}$$

In order to limit the amount by which  $W$  is decreased during each update, take the smaller  $\beta$ .

Multiply by

$$\frac{\sqrt{z^2 + \bar{\alpha}^2}}{\sqrt{z^2 + \bar{\alpha}^2}}$$

$$\beta = \frac{\sqrt{z^2 + \bar{\alpha}^2} - \sqrt{z^2 - \bar{\alpha}^2} - z^2}{z^2 \sqrt{z^2 + \bar{\alpha}^2}}$$

$$= \frac{\sqrt{z^2 + \bar{\alpha}^2} - \bar{\alpha}^2}{z^2 \sqrt{z^2 + \bar{\alpha}^2}}$$

Since  $W^+ = \Delta$        $W^+ = W + \Delta W = W[I - \underline{\beta} \underline{z} \underline{z}^T]$

$$\Delta W = -W \underline{\beta} \underline{z} \underline{z}^T$$

Using (19)

$$\begin{aligned}\Delta W &= -W \left[ \frac{\sqrt{z^2 + \bar{\alpha}^2} - \alpha}{z^2 \sqrt{z^2 + \bar{\alpha}^2}} \right] \underline{z} \underline{z}^T \\ &= -W \underline{z} \underline{z}^T \left[ \frac{\sqrt{(z^2 + \bar{\alpha}^2) - \alpha} (\sqrt{z^2 + \bar{\alpha}^2} + \alpha)}{z^2 \sqrt{z^2 + \bar{\alpha}^2} (\sqrt{z^2 + \bar{\alpha}^2} + \alpha)} \right] \\ &= -W \underline{z} \underline{z}^T \frac{1}{z^2 + \bar{\alpha}^2 + \alpha \sqrt{z^2 + \bar{\alpha}^2}} \\ &= -W \underline{z} \underline{z}^T \frac{1}{(z^2 + \bar{\alpha}^2) \left[ 1 + \sqrt{\frac{\bar{\alpha}^2}{z^2 + \bar{\alpha}^2}} \right]} \quad (21)\end{aligned}$$

Regrouping,

$$\begin{aligned}\Delta W &= \frac{-Wz}{z^2 + \bar{\alpha}^2} \cdot \frac{z^T}{1 + \sqrt{\frac{\bar{\alpha}^2}{z^2 + \bar{\alpha}^2}}} \\ &= \frac{-Wz^T}{1 + \sqrt{\frac{\bar{\alpha}^2}{z^2 + \bar{\alpha}^2}}}\end{aligned}$$

Therefore, from (20) and (21)

$$W^+ = W - \frac{Wz^T}{1 + \sqrt{\frac{\bar{\alpha}^2}{z^2 + \bar{\alpha}^2}}}$$

which is equation (16).

Unknown landmarks.— The orbital navigation program can also use optical marks made on unknown landmarks. In this mode of operation the program uses the first mark to define the location of the landmark.

Following the derivation in reference 3, consider the plane determined by the planet center, landmark, and vehicle shown in figure 2 below.




Figure 2.

By vector addition

$$\underline{r}_\ell = \underline{r}_c + \underline{z} \quad (22)$$

To find  $\underline{z}$  and thus,  $\underline{r}_\ell$ , notice

$$z \cos v + r_\ell \cos \mu = r_c$$

$$z = \frac{r_c - r_\ell \cos \mu}{\cos v} = \frac{r_c}{\cos v} \left[ 1 - \frac{r_\ell}{r_c} \cos \mu \right] \quad (23)$$

Using the law of sines,

$$\frac{\sin \lambda}{r_c} = \frac{\sin v}{r_\ell} \quad \text{and} \quad \sin \lambda = \frac{r_c}{r_\ell} \sin v \quad (24)$$

and using the identity  $\cos^2 \lambda + \sin^2 \lambda = 1$ ,

$$\cos \lambda = \sqrt{1 - \sin^2 \lambda} = \sqrt{1 - \left( \frac{r_c}{r_\ell} \right)^2 \sin^2 v} \quad (25)$$

Now, from the figure

$$\begin{aligned} \cos \mu &= \cos[\pi - (\lambda + v)] = -\cos(\lambda + v) \\ \cos \mu &= \sin \lambda \sin v - \cos \lambda \cos v \end{aligned} \quad (26)$$

Combining (24), (25), and (26)

$$\begin{aligned} \cos \mu &= \frac{r_c}{r_\ell} \sin^2 v + \cos v \sqrt{1 - \left( \frac{r_c}{r_\ell} \right)^2 \sin^2 v} \\ \frac{r_\ell}{r_c} \cos \mu &= \sin^2 v + \cos v \frac{r_\ell}{r_c} \sqrt{1 - \left( \frac{r_c}{r_\ell} \right)^2 \sin^2 v} \end{aligned}$$

Recall equation (23)

$$z = \frac{r_c}{\cos v} \left[ 1 - \frac{r_\ell}{r_c} \cos \mu \right]$$

$$\begin{aligned}
 z &= \frac{r_c}{\cos v} \left[ 1 - \sin^2 v - \cos v \frac{r_\ell}{r_c} \sqrt{1 - \left(\frac{r_c}{r_\ell}\right)^2 \sin^2 v} \right] \\
 &= \frac{r_c}{\cos v} \left[ \cos^2 v - \cos v \frac{r_\ell}{r_c} \sqrt{1 - \left(\frac{r_c}{r_\ell}\right)^2 \sin^2 v} \right] \\
 &= r_c \left[ \cos v - \sqrt{\left(\frac{r_\ell}{r_c}\right)^2 - \sin^2 v} \right]
 \end{aligned}$$

So equation (22) becomes

$$r_\ell = r_c + r_c \left[ \cos v - \sqrt{\left(\frac{r_\ell}{r_c}\right)^2 - \sin^2 v} \right] u_m \quad (27)$$

where  $u_m$  is the measured line of sight.

Looking at the result for the landmark position, equation (27), one notices the  $r_\ell$ , the magnitude of the vector, is required. Since this is unavailable for an unknown landmark,  $r_\ell$ , is taken to be the mean radius of the planet.

This approximation introduces considerable inaccuracies into the landmark position estimate. For the remainder of the marks, the landmark is considered known. The resulting updates decrease the landmark error.

Having reviewed and approved the equations used in P22, this paper will next provide an explanation of the coding of these equations.

## THE CMC CODING

Review of the coding for the orbital navigation program has been accomplished chiefly through analysis of the MIT flow charts and study of the decoding in reference 2. The Program 22 flow charts are presented in Appendix A.

The coding analysis will follow through reference 2 line by line.

Explanation of each line will be given to the right of that line.

1. Start program

PROG 22

## CODE

## EXPLANATION

- |  |  |
|--|--|
| 2. Perform R02                               | 2. IMU STATUS CHECK;   |
|  | if REFSM = 1, IMU orientation<br>is known by computer and proceed.   |
|  | if REFSM = 0 and IMU is on, per-<br>form P51 to determine alignment. |
|  | if REFSM = 0 and IMU is off, go<br>to POS to start up GNCS.          |
| 3. Set TARG2FLG = 1<br>(bit 9 of FLAGWRD 1)  | 3. Target is a landmark.   |
| 4. Set TARG1FLG = 0<br>(bit 10 of FLAGWRD 1) | 4. Target is not LEM.  |
| 5. Set RNDVZFLG = 0<br>(bit 7 of FLAGWRD 0)  | 5. P20 is not running.   |
| 6. $T_{\text{decl}} = T_{\text{now}}$        | 6. Time to which integration is to<br>be performed is present time.  |
| 7. Perform CSM Conic                         | 7. CSM R & V are integrated conically.                               |

8.  $\text{PMGA} = \cos^{-1}[\text{unit } (\underline{v}_{\text{att}} \times \underline{R}_{\text{att}}) \cdot \text{REFSMMAT}_3]$
9. Set RENDWFLG  
(bit 1 of FLAGWRD 5)
10.  $\text{TS} = 0645_{\text{vn}}$
11. Perform GOFLASHR
12.  $\text{TS} = 011_2$  Perform BLANKET
- PROG. 22A
13. MARKINDEX = 5
14.  $\text{TS} = 00011_8$
15. Proceed to GOPERF1
16. If No R52, proceed.  
If Yes R52, perform R52 and R53 within and proceed to 18.
8. Assuming X of spacecraft is in orbit plane, this checks to see if IMU orientation is satisfactory for P22. PMGA (displayed) is maximum middle gimbal angle possible. If  $> 60^\circ$ , and time permits, IMU should be realigned (P52), then key in V37E22E and proceed. If not, proceed.  
Maneuver to acquire landmark.
9. W matrix is invalid.
10. Machine channeling for 8. (display)  
(specifies VN PATTERN for display routine).
11. Display of 8; exit to realign or continue as decided.
12. Display interface routine.
13. Communication cell with R53.
14. Channeling to display.
15. Display interfacing for choice of auto-optics (R52).
16. Monitor and respond to landmark parameters. R53 is called within R52 automatically or by selection of manual optics.  
SCT trunnion or shaft and trunnion may be driven toward CMC's estimate of landmark position.

17. Perform R53
18. NUM8NN = QPRET<sub>mk</sub>
19. NUMBKK = 1
20. S22LOC = SVMRKDAT
21. SVMRKDAT + i = E<sub>MARKSTAT + i</sub>  
i = 0, 1, ...35
22. Perform 22 LMKID.
23. 22LMKID  
a. LANDMARK = bits 9-4 of 22LMBDO
17. Marks are made; then accepted or rejected; up to 5 unrejected marks may be stored.
18. Total number of marks taken = total number of marks taken.
19. Serial no. of mark being processed.
20. Buffer cell location of 1st mark data to be processed.
21. 35 cells divided into 5 sets, 1 for each mark, containing (TIME 2:1) (TIME 1:2) (CDU<sub>y</sub>), (CDUS), (CDU<sub>z</sub>) (CDUT), (CDU<sub>x</sub>) composing a table to avoid loss if restart occurs.
22. --
23. a. ID for first mark is placed in 22 LMBDO and coded as A, B, C, D, and E where  
A = 1 known  
= 2 unknown  
  
B = 1 coordinates stored  
= 2 coordinates not stored  
  
CD = landmark serial number  
  
E = 1 (earth landmark)  
  
and initialized as A = 1,  
B = 1, CD = ID, E = 1



- d. Set bit 9 of OPTMODES = 0
  - e. OPTIND = -1
  - f. Set bit 2 of channel 12 = 0
  - g. Return
26. If ORBWOK (bit 6 of FLAGWORD 3) = 1, set WDIM9INC (bit 9 of FLAGWORD 5) = 1
27. If ORBWOK = 0  
 $W_i = 0$  ( $i = 0, 1, \dots, 53$ )
  - a.  $W_0 = C_{WORBPS}$
  - $W_4 = "$
  - $W_8 = "$
  - $W_{36} = C_{WORBVL}$
  - $W_{40} = "$
  - $W_{44} = "$
  - b. Set ORBWOK = 1
  - c. Set WDIM9INC = 0
28. Perform S22FLAGS
  - a. Perform INSTALL
  - b.  $T_{decl} = E_{S22LOC d_p}$
- d. Optics switched from computer control mode.
  - e. Driving of optics is bypassed.
  - f. Disable optics CDU error counter.
  - g. --
26. If W matrix is valid for orbital navigation, it is set as  $9 \times 9$  for incorporation purposes.
27. If W matrix is invalid for orbital navigation, ...
  - a. Reinitialize upper  $6 \times 9$  to a diagonal in the upper left  $6 \times 6$ .
  - b. W matrix is valid for orbital navigation.
  - c. W matrix is not a  $9 \times 9$  for incorporation purposes.
28. Preparation for integration.
  - a. Grabs integration package and secures it from other users.
  - b. Integration will be up to time of 1 mark, stored in E.

- c. Set bits 5(STATEUP), 3(CSMINT), 2(WDIMEN 9), and 1(WMATINT) of FLAGWRD 3 = 1
  - c. CM permanent state vector and  $9 \times 9$  W matrix are to be integrated.
  - d. Let CONINT (bit 4 of FLAGWRD 3) = 0
  - d. Encke integration.
  - e. Return
  - e. --
29. Set WDIMEN9 (bit 2 of FLAGWRD 3) = 0      29. W matrix is  $6 \times 6$ .
30. If WDIM9INC = 0, set WMATINT (bit 1 of FLAGWRD 3) = 0      30. W matrix is to be integrated.
31. Perform INTEGRV      31. Integration.
32. CSMPOS<sub>\_</sub> = R<sub>\_att</sub>      32. Answer.
33. If LNDKNOWN = 1, proceed to 22LMK1.  
if LNDKNOWN = 0, Proceed      33. If landmark is known, proceed to 22LMK1; otherwise, proceed [We are now treating an unknown landmark]
34. MARKDATA = S22LOC      34. Address of next mark data.
35. W<sub>i</sub> = 0 (i = 54 - 80)
36. W<sub>72</sub> = K<sub>wun</sub>
37. W<sub>76</sub> = K<sub>wun</sub>
38. W<sub>80</sub> = K<sub>wun</sub>
39. [W<sub>8</sub>] = [W<sub>8</sub>] + K<sub>2</sub> [W<sub>0</sub>]
35. - 39. Lower right  $3 \times 3$  of W matrix is initialized for unknown landmark tracking.  
K<sub>2</sub> = 1
40. X<sub>1</sub> = - MARKDATA
41. MARKDOWN = i = E<sub>MARKDATA + i</sub>, (i = 0-6)      40. - 42. Mark data is shoved into buffers for computations.
42. S1 = MARKDATA + 2
43. Perform SXTNB      43. TS converted to double precision for pointing vector computation.

44. Perform NBSM
45.  $\underline{U}_M = TS \text{ [REFSMMAT]}$
46.  $TS_1 = \text{unit } CSMPOS$
47.  $\text{ALPHAV}_z = TS_{1,z}$
48. Perform GETERAD
49.  $ORBCOSA = -\underline{U}_M \cdot TS.$
50.  $\text{ALPHAV} = CSMPOS = |COMPOS|$
- $$\left[ ORBCOSA - \sqrt{\left( \frac{ERADM}{|COMPOS|} \right)^2 - (1 - ORBCOSA)^2} \right] \underline{U}_M$$

51. Delay 2 secs (via DELAYJOB)
52. Proceed to S22B1G2

### S22B1G2

- a. Set ERADFISC  
(bit 13 of FLGWRD1) = 1
- b.  $TS = E_{S22LOC_{dp}}$
- c. Perform LAT - LONG
- d. If  $NUM8NN - NUM8KK \leq 0$ , go to 9DWT06DW
- e.  $NUMBKX = NUMBKX + 1$
- f.  $S22LOC = S22LOC + 7$
- g. Proceed to S22B1G1
- a. Use Fischer ellipsoid radius.
- b. Time of mark.
- c.  $r_1$  converted to latitude, longitude, and attitude.
- d. If this is last mark, go to .....
- e. Serial number of mark date is increased by one.
- f. Starting address of next mark data.
- g. --

[Now if we had marked on a known landmark, we would be back at 33 and starting 22LMK1]

#### 22 LMK1

- a. If LNDMKS (bit 7 of FLAGWRD2) = 0, proceed to 22LMKDAT; otherwise, proceed.
- b. TS = bits 14 - 4 of 22LMB00, shifted right 3 places
- c. X1 = LLATAB + 6TS
- d. LAT =  $E_{X1}$
- e. Proceed to S22.16A
- a. If landmark coordinates are not stored, ....
- b. --
- c. Address of landmark table entry.
- d. Latitude, longitude, and altitude stored.
- e. --

[If coordinates had not been stored in a above]

#### 22LMKDAT

- a. LANDALT = ALT/ $K_{2dcptl}$
- b. LANDLONG = 1/2 LONG
- c. TS = 0689<sub>vn</sub>
- d. Proceed to GOFLASH;
  - (1) If terminate proceed to GOTPOOH
  - (2) If proceed, proceed to S22.16
  - (3) Otherwise, proceed.
- e. ALT =  $K_{2dcptl}$  LANDALT
- f. LONG = 2LONDLONG
- a. Scale altitude for display; store in LANDALT.
- b. Longitude/2 displayed for better accuracy.
- c. Channeling for display.
- d. Display of landmark coordinates.
- (2) if accept data, ...
- (3) if reject data, ...
- e., f. Data has been modified. This is rescaling as above.

g. Proceed to c

g. Recycle from c till satisfied.

S22.16A

a.  $w_i = 0$  ( $i = 54-80$ )

b.  $w_{72} = C_{Wmk}$

c.  $w_{76} = C_{Wmk}$

a-d. Initialize lower right  
3 x 3 for known landmark  
incorporation.

d.  $w_{80} = C_{Wmk}$

e. If LNDMKSTR = 1,  
 $[w_8] = K_{3d4} [w_8]$

e. If landmark is stored,  
reduce  $w_8$ .

f. Proceed to S22BI61.

f. --

S22B1G1

- 53. Set ERADFISC  
(Bit 13 of FLAGWRD 1) = 1
- 54. TS =  $E_{S22LOC_{dp}}$
- 55. Perform LALOTORV
- 56.  $X789 = K_{rfactl} \text{ ALPHAV}$
- 57. Perform S22FLAGS
- 58. Perform INTEGRV
- 59.  $CSMPOS = R_{att}$
- 60. MARKDATA = S22LOC
- 61.  $X1 = - MARKDATA$
- 62.  $MARKDOWN + i = E_{MARKDATA + i}$   
 $i = (0 - 6)$
- 63.  $S1 = MARKDATA + 2$
- 53. Use Fischer ellipsoid radius  
for coordinate computations.
- 54. Time of mark.
- 55. Gets  $A_x$ ,  $A_y$ ,  $A_z$ , and  $r_l$ .
- 56. Rescales  $r_l$  to kilometers.
- 57. Sets flags for and time of next  
mark for integration.
- 58. W matrix and CSM vector are inte-  
grated to specific time.
- 59. Answer.
- 60. Address of next mark data.
- 61-63. Mark data is shoved into  
buffers for computations.

64. Perform SXTNB                            64. TS converted to double precision  
for pointing vector computation.
65. Perform NBSM                            65. Computes pointing vector in IMU  
coordinates.
66.  $\underline{U}_M = \underline{TS}$  [REFSMMAT]                    66. Pointing vector in NBY coordinates.
67.  $RCLP = X789 - K_{rfactl} CSMPOS$             67. Relative landmark vector.
68. Set FSTINCRP = 1  
(bit 11 of FLAGWRD5)                    68. First incorporation of measure-  
ment data is being made.
69.  $\underline{TS} = RCLP * \text{UNIT } \underline{Z}$                     69. TS now contains star unit vector  
 $\underline{U}_s^{(o)}$ .
70. If  $|\underline{TS}| < 2^{-6}$  km,  $\underline{U}_{\text{STAR}} =$   
 $\text{UNIT } \underline{Y}$                                     70. If 69 overflows,  $\underline{U}_s^{(o)} = \begin{bmatrix} 0 \\ 1 \\ 0 \end{bmatrix}$   
NBY
71. If  $|\underline{TS}| \geq 2^{-6}$  km,  $\underline{USTAR} =$   
 $\text{UNIT } \underline{TS}$                                     71. If 69 doesn't overflow, ....
72. Proceed to S22B164                            72. --

S22B164

73. VARIANCE =  $(RCLP)^2 (K_{SCTVAR} + \frac{\alpha^2}{K_{IMUVAR}})$                     73.  $\bar{\alpha}^2$
74. Perform BVECTORS                            74. --
75. BVECTORS                                    75. BVECTOR and other intermediate  
Kalman computations.
- a.  $\text{BVECTOR}_{-0} = \text{unit}(\text{UNIT } RCLP * \underline{USTAR})$
- b.  $\underline{USTAR} = \text{BVECTOR}_{-0}$
- c.  $\text{DELTAQ} = K_{2\pi} |RCLP|$   
 $[\cos^{-1} (\text{BVECTOR}_{-0} \cdot \underline{U}_M) - 1/4],$   
 $(1/4 = 90^\circ)$

- d.  $\text{BVECTOR}_{-1} = 0$
  - e.  $\text{BVECTOR}_{-2} = 0$
  - f. RETURN
76.  $\text{BVECTOR}_{-2} = -\text{USTAR}$       76. BVECTOR for update of landmark.
77. Set WD1M91NC (bit 9 of FLAGWRD5) = 1      77. W matrix is  $9 \times 9$  for incorporation purposes.
78. Set CSMUPDT (bit 8 of FLAGWRD1) = 1      78. CSM state vector is to be updated.
79. Perform INCORP1      79. --
80. INCORP1      80. --
- a.  $\underline{z}_0 = [W_0] \text{BVECTOR}_{-0} + [W_3] \text{BVECTOR}_{-1} + [W_6] \text{BVECTOR}_{-2}$       a-c. Computation of  $\underline{z}$ , where  $\underline{z} = W^T \underline{b}$
- b.  $\underline{z}_1 = [W_1] \text{BVECTOR}_{-0} + [W_4] \text{BVECTOR}_{-1} + [W_7] \text{BVECTOR}_{-2}$
- c.  $\underline{z}_2 = [W_2] \text{BVECTOR}_{-0} + [W_5] \text{BVECTOR}_{-1} + [W_8] \text{BVECTOR}_{-2}$
- d. If WD1M91NC = 0,  
 $\underline{z}_2 = 0$       d. If W matrix is not a  $9 \times 9$  for incorporation purposes.
- e. LITLA =  $\underline{z}_0^2 + \underline{z}_1^2 + \underline{z}_2^2$   
+ VARIANCE      e.  $z^2 + \bar{\alpha}^2$
- f. TS =  $\sqrt{\text{LITLA VARIANCE}}$       f-h. Intermediate steps in computing the Kalman.
- g. GAMMA =  $1/(TS + \text{LITLA})$
- h. DELQDA = DELTAQ/LITLA

- i.  $\text{OMEGA}_{-0} = z_0 [w_0] + z_1 [w_1] + z_2 [w_2]$
- j.  $\text{OMEGA}_{-1} = z_0 [w_3] + z_1 [w_4] + z_2 [w_5]$
- k.  $\text{OMEGA}_{-2} = z_0 [w_6] + z_1 [w_7] + z_2 [w_8]$
- l.  $\text{DELTA } \underline{x}_0 = \text{DELQDA } \text{OMEGA}_{-0}$
- m.  $\text{DELTA } \underline{x}_1 = \text{DELQDA } \text{OMEGA}_{-1}$
- n.  $\text{DELTA } \underline{x}_2 = \text{DELQDA } \text{OMEGA}_{-2}$
- o. RETURN

- 81.  $DSTEML_{dp} = K_{kmmtr} 2$   
| $\text{DELTA } \underline{x}_0$ |
- 82.  $DSTEML + 2_{dp} = K_{kmmcs} 2$   
| $\text{DELTA } \underline{x}_1$ |
- 83.  $TS = 0649_{vn}$
- 84. Perform GOFLASHR  
If terminate, proceed to  
fourth line of S22B1G2;  
if proceed, go to 87;  
otherwise, proceed
- 85.  $TS = 00_2$  and perform BLANKET
- 86. END of JOB
- 87. Perform INCORP2
- 81,82. Scaling for display.
- 83-85. Display routines and incorporation decision.
- 86. --
- 87. --

88. INCORP2

- a. EGRESS = return address
- b. Perform INTSTALL
- c.  $\underline{\text{OMEGAM}}_0 = \text{GAMMA } \underline{\text{OMEGA}}_0$
- d.  $\underline{\text{OMEGAM}}_1 = \text{GAMMA } \underline{\text{OMEGA}}_1$
- e.  $\underline{\text{OMEGAM}}_2 = \text{GAMMA } \underline{\text{OMEGA}}_2$
- f. Set INTPHS (bit 13 of FLAGWRD5) = 1
- g.  $[W_0] = [W_0] - \underline{Z}_0 \text{ OMEGAM}_0$
- h.  $[W_1] = [W_1] - \underline{Z}_1 \text{ OMEGAM}_0$
- i.  $[W_3] = [W_3] - \underline{Z}_0 \text{ OMEGAM}_1$
- j.  $[W_4] = [W_4] - \underline{Z}_1 \text{ OMEGAM}_1$
- k. If WDLM91NC = 1,  
 $[W_2] = [W_2] - \underline{Z}_2 \text{ OMEGAM}_0$   
 $[W_5] = [W_5] - \underline{Z}_2 \text{ OMEGAM}_1$   
 $[W_6] = [W_6] - \underline{Z}_0 \text{ OMEGAM}_2$   
 $[W_7] = [W_7] - \underline{Z}_1 \text{ OMEGAM}_2$   
 $[W_8] = [W_8] - \underline{Z}_2 \text{ OMEGAM}_2$

- l. If CSMUPDT = 1  
(bit 8 of FLGWRD1)

## 88. --

- a. --
- b. Grabs and secures orbital package for matrix updating procedures.
- c-e. --
- f. To preclude loss of integrating package to priority if a restart occurs.
- g-j. W matrix is updated.
- k. Additional W matrix updating for a 9 x 9
- l. If the CSM state vector is to be updated, do so.

- (1)  $TS_{-1} = \text{DELTAV}_{\text{-cm}} + \text{DELTAX}_{\text{-o}}$  (1)-(3). For no overflow condition add weighted residual to perturbation portion of vector.
- (2)  $TS_{-2} = \text{NUV}_{\text{-cm}} + \text{DELTAX}_{-1}$
- (3) If there is no overflowing in computing  $TS_{-1}$  and/or  $TS_{-2}$ :  
 $\text{DELTAV}_{\text{-cm}} = TS_{-1}$   
 $\text{NUV}_{\text{-cm}} = TS_{-2}$
- (4) If overflow has occurred in computing  $TS_1$  and/or  $TS_2$ :  
 $R_{\text{-rectcm}} = RVC_{\text{cm}} + \text{DELTAV}_{\text{cm}} + \text{DELTAX}_{\text{-o}}$   
 $RCV_{\text{-cm}} = R_{\text{-rectcm}}$   
 $V_{\text{-rectcm}} = VCV_{\text{-cm}} + \text{NUV}_{\text{cm}} + \text{DELTAX}_{-1}$   
 $VCV_{\text{-cm}} = V_{\text{-rectcm}}$   
 $\text{DELTAV}_{\text{-cm}} = 0$   
 $\text{NUV}_{\text{cm}} = 0$   
 $T_{\text{ccm}} = 0$   
 $XKEP_{\text{cm}} = 0$  (4) For overflow condition add weighted residual to the whole state vector, i.e., the conic portion plus the perturbed portion, and consider this update as a new rectification.
- (5) If  $WD1M91NC = 1$  (5) If matrix is  $9 \times 9$ , update the landmark coordinates.  
 $X \underline{789} = X \underline{789} + \text{DELTAX}_{-2}$

(6) Perform PTOACSM

(6) New vector is labeled as the permanent state vector.

(7)  $\underline{R} = K_{rfctr} (\underline{RCV} + \underline{TDELTAV})$ 

(7)-(9) --

(8)  $\underline{V} = K_{vfctr} (\underline{VCV} + \underline{TNUV})$ (9)  $T_{pptm} = T_{et}$ 

m. If CSMUPOT = 0

m. If LM state vector is to be updated, perform 1, but with LM vectors.

n. QPRET = EGRESS

n. --

o. PROCEED TO INTWAKE

o. Which returns

89.  $CSMPOS_{cm} = K_{lkb\ 15} (\underline{RCV}_{cm} + \underline{DELTAV}_{cm})$ 

89. CSM position vector rescaled

90. If FSTINCRP (bit 11 of FLAGWRD 5) = 1  
     $RCLP = X \underline{789} - K_{rfact1} CSMPOS$ 

90. If first incorporation of a measurement, compute relative landmark position and recycle to S22B164

Proceed to S22B164

91. Proceed to S22B162.

91. Recycle to S22B162 to process next mark

[Within S22B162.

52.d. If  $NUM8NN - NUM8KK \leq 0$ ,

] [If all marks have been processed go to 9DWT06DW]

92. 9DWT06DW92. Converts upper  $6 \times 9$  of  $9 \times 9$  matrix to an equivalent  $6 \times 6$

93. S22.1P5

- a. If LNDMKSTR = 0  
(bit 7 of FLAGWRD 2)
  - (1) If 22LMB0 =  $K_{22\text{mdmx}}$ ,  
22LMBDO = 0
  - (2) If 22LMBD  $\neq K_{22\text{mbmx}}$ ,  
22LMBDO = 22LMBD
- b. Proceed to S22EX3

## 94. S22EX3

- a. LANDMARK = 22LMBDO
- b. Proceed to S22EX33

95. S22EX33

- a. TS = 6570<sub>vn</sub>
- b. Perform GOFLASHR
  - (1) If terminate, proceed to 22TERM,
  - (2) If proceed, go to 1;
  - (3) otherwise, proceed to S22EX3
- c. TS = 101<sub>2</sub> and perform BLANKET
- d. End of job
- e. LANDALT = ALT/ $K_{2\text{dcptle}}$
- f. LANDLONG = 1/2 LONG

## 93.

- a. If landmark is not stored, serial number of cell where landmark data is stored is kept as one, since only one landmark can be stored in Sundisk

b. --

## 94.

- a. Landmark code = number in 22LMBDO
- b. --

## 95.

- a. For display of landmarks ID.
- b. --
  - (1) If one does not wish to see display of updated landmark, ...
  - (2) If one wishes to see them, ...
  - (3) Otherwise, recycle....
- c. Kills display
- d. --
- e. Scaling for display
- f. For display

- g.  $TS = 0689_{vn}$
- h. Proceed to GOFLASH;
- (1) if terminate, proceed to 22TERM;
  - (2) if proceed, proceed;
  - (3) otherwise, go to i.
- i.  $TS = \text{bits } l4\text{-}4 \text{ of } 22LMBDO,$   
right shifted 3 places
- j.  $Xl = LLATAB + 6 TS$
- k.  $E_{Xl} = LAT$
- l. If LNDMKSTR (bit 7 of flagword 2) = 0  
 $22LMBDO = 22LMBDO + K_{lbl1}$
- m. Proceed to 22TERM
96. 22TERM
- a.  $TS = 00017_8$
  - b. Proceed to 60PERF1;
- (1) If terminate, proceed to GOTPOOH;
  - (2) If proceed, proceed to GOTPOOH;
  - (3) Otherwise, proceed to PROG22A
- g. Verb-noun flash for display of updated landmark coordinates
- h.
- (1) If one doesn't want updated landmark coordinates to be stored as the landing site, ....
  - (2), (3) --
- i-k. Landmark data is stored.
- l. If landmark is not tagged as stored, indicate that one has now been stored.
- m. --
- 96.
- a. --
  - b.
- (1) and (2) P22 is finished.
  - (3) Recycle to perform another sighting

### Results of Coding Review

Flow chart comparison.- A comparison of the above coding and the MIT flow charts in appendix A reveals no differences except occasional insignificant order changing of steps and the omission of the W<sub>8</sub> downgrade (page 9 of appendix A) for a stored landmark in the coding. In this latter instance, as at other times during the review, reference to the actual SUNDISK revision 282 listing was used to resolve difficulties. The W<sub>8</sub> downgrade is not contained in the 282 listing.

Comparison of equation and astronaut procedure to coding.- Besides the comparison between coding and flow charts, checks have been made between coding and equations, and coding and astronaut procedural interfaces, as outlined in reference 5 and reproduced in appendix B. In all instances, the comparisons were satisfactory. P22's interfaces with R52, R53, R02, CSMCONIC, P52, and P00 also appear satisfactory.

Illegal interfaces.- Not all interfaces with P22 are valid, however. Generally, none of the P30's or P40's (P3X or P4X) should be called while P22 is running, or vice versa, due to shared erasable cells (ref. 6). Verb 82 cannot be used during P22 for the same reason (ref. 7). Programs 22 and 20 cannot be operated simultaneously since P22 initializes the W matrix to a 9-by-9 (ref. 8). Program 22 or any program cannot be called by verb 37 if integration is in process, or in P05 until the time specified in reference 8. Before running any program, reference 8 and its updates should be read.

### ASTRONAUT PROCEDURES

Crew procedures for exercising the orbital navigation program are presented in appendices B and C. Appendix B contains the procedures and interfaces among the crew, CMC, and the ground, as written by MIT in reference 5. Appendix C gives the concentrated crew procedures for P22 which are to be carried onboard the CM during Apollo 7 (ref. 9).

Comparison of appendices B and C reveals no differences save the omission of the IMU status check (R02) in appendix C.

### BIT-BY-BIT TESTING

The final "roped" version of SUNDISK 282 has been tested on the MSC bit-by-bit simulator. This simulator contains an exact representation of the CMC, i.e., the machine language coding is the same.

Results of the bit-by-bit tests for orbital navigation are contained in appendices D and E. The tables (ref. 10) contain comparisons between the W-matrix, b-vector, and state vectors as computed by SUNDISK 282 P22 and by a reliable onboard bench program outlined in reference 3.

Two bit-by-bit cases were run. The first case (appendix D) involved sightings on two known landmarks. The second case (appendix E), is a rerun of the first case with the first landmark considered unknown. In both cases, only three marks could be taken on the second landmark due to constraints within the environmental program associated with the bit-by-bit simulator.


For both cases the results are excellent. Differences between the SUNDISK program and the engineering simulations are small and can be attributed to differences between fixed and floating point machines. These results, added to other studies of P22 with the engineering simulator, indicate the program operates correctly and performs well in flight configuration.


#### CONCLUSION


From the study of equations, coding, astronaut procedures, and testing which has been presented, SUNDISK 282 orbital navigation program. P22 has been verified as valid for earth orbital flight.


APPENDIX A


MIT FLOWCHARTS FOR SUNDISK REV 212 P22









































|                      |                      |                                     |
|----------------------|----------------------|-------------------------------------|
| INSTRUMENTATION LAB  |                      | APOLLO<br>TELESCOPIC AND NAVIGATION |
| CAMBRIDGE, MASS.     |                      | P22                                 |
| DRAWN BY PEPPERSON   | 7-1-67               | ORBITAL NAVIGATION                  |
| PROG NO. 22          | 1-1-67               | DOCUMENT NO.                        |
| ANALYSTS J. L. LANCE | 7-7-67               | FC 0590                             |
| TESTED               | SUNDAY 282           |                                     |
| USED ON APRIL 1967   | 8-7-67 REV 1 1974-68 | SHEET 13 OF 18                      |






|                     |   |                                   |
|---------------------|---|-----------------------------------|
| 197                 | INSTRUMENTATION LAB<br>CAMBRIDGE, MASS. | APOLLO<br>GUIDANCE AND NAVIGATION |
| DRAWR [Signature]   | 7-7-67                                  | P22                               |
| PRGRM [Signature]   | 1-2-67                                  | ORBITAL NAVIGATION                |
| ANALYST [Signature] | 1-2-67                                  | SUNDESK 292 DOCUMENT NO.          |
| DOC/NR              |   | FC 0590                           |
| USED ON             | APPROV [Signature] 8-7-67               | REV 1 17 APR 68 SHEET 18 OF 18    |



## MATRIX CONVERSION ROUTINE

FROM PRECEDING PAGE

CONTINUE NEXT ROW  
IN W MATRIX

|                      |                         |
|----------------------|-------------------------|
| INSTRUMENTATION LAB  | AMMO                    |
| CAMBRIDGE, MASS.     | GUIDANCE AND NAVIGATION |
| DEAN: E. PEARSON     | 7-11-6                  |
| PRIMER: R. SPINN     | 5-1-6                   |
| ANALYST: G. HARRIS   | 7-1-6                   |
| ORIGIN:              | SUNDISK 282             |
| DISP ON: APPROX      | 6-7-67 REV 1 17 JAN 68  |
| DOCUMENT NO. FC 0590 |                         |
| SHEET 17 OF 18       |                         |

P22

ORBITAL NAVIGATION

## MATRIX CONVERSION ROUTINE

STEP 3, ORDER MATRIX IN STANDARD MANNER. FINAL RESULT IS OF THE FORM

$$W = \begin{pmatrix} W_0 & W_1 & W_2 & W_3 & W_4 & W_5 \\ W_1 & W_4 & W_7 & W_{10} & W_{13} & 0 \\ W_2 & W_5 & W_8 & W_{11} & 0 & 0 \\ W_3 & W_{10} & W_{13} & 0 & 0 & 0 \\ W_4 & W_{11} & W_{14} & 0 & 0 & 0 \\ W_5 & 0 & 0 & 0 & 0 & 0 \end{pmatrix}$$

PAGEN21  
 W27 ← W3  
 W28 ← W4  
 W29 ← W5  
 W33 ← W15  
 W34 ← W16  
 W35 ← W17  
 W3 ← W6  
 W4 ← W7  
 W5 ← W8  
 W15 ← W30  
 W16 ← W31  
 W17 ← W32  
 W6 ← W12  
 W7 ← W13  
 W8 ← W14  
 W30 ← W9  
 W31 ← W10  
 W32 ← W11  
 W9 ← W18  
 W10 ← W19  
 W11 ← W20  
 W12 ← W24  
 W13 ← W25  
 W14 ← W26  
 W18 ← 0  
 W19 ← 0  
 W20 ← 0  
 W24 ← 0  
 W25 ← 0  
 W26 ← 0

CLRWWWW

CLEAR  
W<sub>60</sub> TO W<sub>69</sub>

CLEAR MATRIX TEMPORARY STORAGE

END OF MATRIX CONVERSION ROUTINE

S22.IPS  
SH12

|                  |                |                                   |
|------------------|----------------|-----------------------------------|
| DISTRIBUTION LAB | BIT            | APOLLO<br>GUIDANCE AND NAVIGATION |
| CAMBRIDGE, MASS. |                |                                   |
| BRAUN, J. PEGG   | 7-2-67         |                                   |
| POGUE            | 5-2-67         |                                   |
| ANALYST          | <i>J. Bunn</i> | P22                               |
| DISCPMR          |                | ORBITAL NAVIGATION                |
| USED ON          | APPN           | SUNDISK 282                       |
|                  | 7-24-70        | DOCUMENT NO.<br>FC 0590           |
|                  |                | REV 1 17 JAN 69                   |
|                  |                | Sheet 10 of 10                    |

APPENDIX B

MIT APOLLO COMPUTER LOGIC CHECKLIST INTERFACE

(GSOP IV)

AERIAL NAVIGATION PROGRAM (P22)

LOGIC REV 26 03/07/68  
CHECKLIST REV 29 06/06/68

PURPOSE

(1) TO LOCATE AND TRACK A LANDMARK SUITABLE FOR NAVIGATION PURPOSES. ACQUISITION MAY BE AIDED BY THE CMC WITH THE OPTICS AUTOMATICALLY POINTED AT A "KNOWN" (SEE ASSUMPTIONS BELOW) LANDMARK WHOSE LATITUDE, LONGITUDE, AND ALTITUDE HAVE BEEN KEYED INTO THE USKY BY THE ASTRONAUT. IT MAY ALSO BE DONE BY THE ASTRONAUT WITH THE OPTICS MANUALLY POINTED AT A "KNOWN" LANDMARK PREDETERMINED BY THE ASTRONAUT OR A "KNOWN" OR "UNKNOWN" (SEE ASSUMPTION BELOW) LANDMARK SELECTED AT WILL DURING SEARCH FOR TARGETS OF OPPORTUNITY.

(2) TO OBTAIN SIGHTING MARKS ON THE CHOSEN LANDMARK.

(3) TO CALCULATE THE ORBITAL PARAMETER CHANGES GENERATED BY THE LANDMARK SIGHTING.

(4) TO DISPLAY THE ORBITAL PARAMETER CHANGES GENERATED, FOR DECISION AS TO THEIR VALIDITY BY THE ASTRONAUT/GROUND BEFORE THEIR INCORPORATION INTO THE CMC CALCULATION OF SC POSITION AND VELOCITY.

(5) TO PROVIDE UPDATED COORDINATES OF THE KNOWN LANDMARKS.

(6) TO PROVIDE COORDINATES OF UNKNOWN LANDMARKS (LANDMARK DESIGNATION ROUTINE).

ASSUMPTIONS: (1) THERE ARE TWO TYPES OF LANDMARK TRACKING METHODS:

(A) "KNOWN" LANDMARK TRACKING--THE TRACKING OF A LANDMARK IDENTIFIED TO THE CMC BY LATITUDE, LONGITUDE, AND ALTITUDE AFTER THE MARKS ARE COMPLETE.

(B) "UNKNOWN" LANDMARK TRACKING--THE TRACKING AND MARKING OF A LANDMARK OR SURFACE FEATURE IDENTIFIED TO THE CMC ONLY AS AN UNKNOWN LANDMARK.

(2) DURING THIS PROGRAM THE UNCS HAS THE CAPABILITY FOR ATTITUDE CONTROL OF THE VEHICLE. POSSIBLE ATTITUDE CONTROL METHODS MIGHT BE AS FOLLOWS (IN ALL CASES CARE MUST BE TAKEN TO MONITOR POSSIBLE IMPENDING IMU GIMBAL LOCK).  
      (A) MANUAL CONTROL BY THE PILOT OR NAVIGATOR WITH THE ROTATIONAL HAND CONTROLLER.

(B) MANUAL RATE CONTROL BY THE NAVIGATOR WITH THE MINIMUM IMPULSE CONTROL IN THE GNC FREE MODE.

(3) THE PROGRAM MAY BE PERFORMED WITH SIVB ATTACHED IF THE LAUNCH VEHICLE GUIDANCE SWITCH IS PLACED IN THE CMC POSITION THEREBY PERMITTING SIVB ATTITUDE CONTROL WITH THE ROTATIONAL CONTROLLER. GNC A/P CONTROL IS REQUIRED IN THIS CASE

(4) THE UNCS STARTUP AND CHECKOUT PROGRAM (P05) AND THE INFLIGHT ALIGNMENT-IMU ORIENTATION DETERMINATION PROGRAM (P51) MUST BE COMPLETED BEFORE THE COMPLETION OF THIS PROGRAM.  
      THE ISS MAY BE:  
          (A) OFF (STANDBY).  
          (B) ON, AND NOT ALIGNED SINCE TURN ON.  
          (C) ON AND AT AN INERTIAL ORIENTATION KNOWN ONLY INACCURATELY BY THE CMC, I.E. HAVING BEEN ALIGNED AT LEAST ONCE SINCE TURN ON BUT NOT WITHIN THE LAST 3 HOURS.  
          (D) ON AND AT AN INERTIAL ORIENTATION KNOWN ACCURATELY BY THE CMC, I.E. HAVING BEEN ALIGNED WITHIN THE LAST 3 HOURS.

IF (A) IS TRUE AND P22 IS SELECTED, THE CMC WILL REQUEST SELECTION OF P05.  
IF (B) IS TRUE AND P22 IS SELECTED, THE CMC WILL REQUEST SELECTION OF P51.  
IF (C) IS TRUE THE CMC MAY OR MAY NOT HAVE A SATISFACTORY INERTIAL REFERENCE.  
IF (D) IS TRUE THE CMC HAS A SATISFACTORY INERTIAL REFERENCE.

(5) THE GROUND TRACK DETERMINATION PROGRAM P21 IS AVAILABLE TO AID THE CREW IN THE SELECTION OF APPROPRIATE LANDMARKS PRIOR TO THE SELECTION OF P22 AND TO PROVIDE UPDATED GROUND TRACK INFORMATION AFTER THE COMPLETION OF P22.

(6) THE PROGRAM IS SELECTED BY THE ASKONNAIT BY OSKÝ ENTRE

| PROG COUNT | CMC | GROUND | CREW | CHECKLIST  | TIME | TOTAL TIME |
|------------|-----|--------|------|--|------|------------|
|            |     |        |      | - CREW PROG<br>- SELECTION<br>...  |      |            |
|            |     |        |      | - KEY IN ORBITAL<br>NAVIGATION PROGRAM<br>(P22)<br>DISPLAY PROGRAM 22  |      |            |
|            |     |        |      | - V 37 E 22 E  |      |            |
|            |     |        |      | -  |      |            |
|            |     |        |      | - MONITOR DSKY:<br>OBSERVE DISPLAY<br>OF PROGRAM 22  |      |            |
|            |     |        |      | -  |      |            |
|            |     |        |      | - DO IMU STATUS CHECK<br>ROUTINE (R22)   |      |            |
|            |     |        |      | -  |      |            |
|            |     |        |      | - THE FOLLOWING ARE REQUIRED:<br>CMC - ON<br>IMU - ON<br>SCS - ON<br>G/N PWR - AC1<br>G/N PWR OPTICS - ON<br>OPTICS MODE - MAN<br>THEN ZERO (15 SEC) |      |            |
|            |     |        |      | - MANEUVER CSM TO ATTITUDE<br>DESIRED FOR LMK ACQUISITION:   |      |            |
|            |     |        |      | 1. USE RHC TO ALIGN SHAFT AXIS<br>IN ORBITAL PLANE AND APPROX<br>10 DEGREES FORWARD OF LOCAL<br>VERTICAL (MAINTAIN COAS ON<br>HORIZON)               | \$10 |            |
|            |     |        |      | 2. USE MIN IMPULSE CNT TO<br>MAINTAIN SC PITCH RATE TO<br>OFFSET ORBITAL RATE  |      |            |
|            |     |        |      | 3. ROLL CSM AS REQUIRED TO AVOID<br>SHAFT AXIS PASSING WITHIN 10<br>DEGREES OF LMK   | \$20 |            |
|            |     |        |      | - KEY V37E 22E   |      |            |

REST AENUEZVIIUS  
FLAÜ

III PERFORM IMU STATUS CHECK  
ROUTINE (RC2)

COMPUTE ANGLE BETWEEN Y AND V X R.  
-SN -  
THIS ANGLE IS THE MAXIMUM MIDDLE GIMBAL ANGLE POSSIBLE ASSUMING THE SC X AXIS IS KEPT IN THE ORBITAL PLANE.

FLASH VÉKU-NUUN TC  
 RÉQUEST RÉPONSE ANN  
 DISPLAY MAX POSSIBL  
 MIDDLE GIMBAL ANGLÉ  
 IF THE X AXIS IS  
 HELD IN THE URBIT  
 PLANE.  
 VÜ6 N45  
 K1:BLANK  
 K2:BLANK  
 K3:MGA  
 IN DEG. TC NEAR-  
 EST -01 DTH

|   |  |   |                              |                                   |
|---|--|---|------------------------------|-----------------------------------|
| MONITOR OSKY:<br>OBSERVE VERA-NOUN<br>FLASH TO REQUEST RE-<br>SPONSE AND DISPLAY<br>OF MAX POSSIBLE | MIDDLE GIMBAL ANGLE<br>IF THE SC X AXIS IS<br>KEPT IN THE CRBIT<br>PLANE | IV<br>CHECK CMC FLASHES VERB-DUN TO<br>REQUEST RESPONSE AND DISPLAYS<br>MAXIMUM MIDDLE GIMBAL ANGLE IF THE<br>SC X AXIS IS KEPT IN THE ORBIT<br>PLANE | FL VO6 N45<br>BLANK<br>BLANK | MAX MGA<br>MAX MGA<br>xxxx.xx DFG |
|---|--|---|------------------------------|-----------------------------------|

IS MGA GREATER THAN  
60 DEG? IF SO, IT IS  
ADVAILABLE TO REALIGN  
THE IMU IF TIME PER-  
MITS.

2

SAIT FÜR KEYBOARD  
STANLY:

-----  
HAS ISS BEEN  
ALIGNED IN PAST  
3 HOURS?

IV CHECK CMC FLASHES VERB-NOUN TO  
 REQUEST RESPONSE AND DISPLAYS  
 MAXIMUM MIDDLE GIMBAL ANGLE IF THE  
 SC X AXIS IS KEPT IN THE ORBIT  
 PLANE

FL V06 N45  
 BLANK  
 BLANK  
 MAX MGA

XXXX-XX OFG

ADVISE CREW  
ON ANTICIPATED CMC  
ERRORS AND SUBSEQUENT PROCEDURES

ACCEPT:  
(NO IMU REALIGNMENT NEEDED)  
PRO

MANEUVER TO ACQUIRE LANDMARK

REJECT:  
(MAX MGA GREATER THAN 60 DEGREES  
OR IMU NOT ALIGNED IN PAST 3 HOURS)

SELECT IMU  
REALIGN (P52).  
WHEN COMPLETE,  
KEY IN V37E22E.

WHEN ALIGNMENT IS COMPLETE  
RESELECT P22.

EXIT P22

TERMINATE FLASH UPON RECEIPT OF PROCEDED OR NEW PROGRAM

KEY IN PROCEED

P NEW  
R PROG  
Q  
G  
E  
E  
C  
EXIT  
P22

"A"  
SEE BELOW

"A"  
SEE BELOW

FLASH VERB-NOUN TO  
HULU  
REQUEST PLEASE  
PERFORM AUTO OPTICS  
SNAP  
VSG N25  
R1:BLANK  
R2:BLANK  
R3:BLANK

MONITOR DSKY:  
OBSERVE VERB-NOUN  
FLASH TO REQUEST  
PLEASE PERFORM AUTO  
OPTICS POSITIONING

FL V50 N25  
00011  
BLANK  
BLANK

CHECK CMC FLASHES VERB-NOUN TO  
REQUEST AUTO OPTICS POSITIONING

FL V50 N25

#148

SET SIGHTING FLAG TO  
LMK FOR USE BY  
SIGHTING MARK AND  
AUTO OPTICS POSITION-  
ING ROUTINES.

#150

SET MARK INDEX TO 5  
FOR USE BY SIGHTING  
MARK ROUTINE (RS3)

WAIT FOR KEYBOARD  
ENTRY:

DO I WISH TO POSITION  
OPTICS AUTOMATICALLY?

#160

Y .N

ACCEPT:

OPTICS MODE - CMC

ENTR

PERFORM AUTO OPTICS POSITIONING  
ROUTINE (RS2)

67

#170

KEY IN  
ENTER

REJECT:

PRO

SET OPTICS MODE SW TO MAN  
ACQUIRE LANDMARK MANUALLY  
GO TO STEP VI

TERMINATE FLASH UPUN  
RECEIPT OF ENTER  
CK PROCEED

#180

.E .P  
.N .R  
.T .C  
.F .C  
.R .E  
.E .D  
.D .D

USE SCT TO ACQUIRE  
A LANDMARK

#190

68

IS LANDMARK SUFFICIENTLY IDENTIFIABLE TO TAKE MARKS?

N Y

DO I WISH TO  
CONTINUE EFFORT  
TO TRACK A  
LANDMARK?

SELECT NEW  
PROGRAM

EXIT  
P22

DO AUTO OPTICS  
POSITIONING  
ROUTINE (R52).  
INCLUDES SIGHTING  
MARK ROUTINE  
R53.

DO AUTO OPTICS  
POSITIONING  
ROUTINE (R52).  
INCLUDES SIGHTING  
MARK ROUTINE  
R53.

DO SIGHTING MARK  
ROUTINE (R53)

DO SIGHTING MARK  
ROUTINE (R53)

VI PERFORM SIGHTING MARK ROUTINE  
(R53)

#200

#210

#220

#240

FLASH VEMB-NOUN  
TC REQUEST RESPONSE  
AND DISPLAY LMK DATA  
\$NAP  
R1-BLANK  
A2-ABCDE  
R3-BLANK  
A2=1 IF KNOWN LMK  
A2=2 IF UNKNOWN N  
LMK  
B=1 IF LMK COOR-  
DINATES ARE STUR-  
ED  
B=2 IF LMK COOR-  
DINATES ARE NOT  
STORED  
CD= LMK ID NO. N  
E=1 IF EARTH LMK  
E=2 IF LUNAR LMK

\*+  
\*26  
\*28  
\*\*

MONITOR DSKY:  
OBSERVE FLASHING  
VERB-NOUN TO REQUEST.  
RESPONSE AND DISPLAY.  
LMK DATA  
R2=A=1 IF KNOWN LMK  
A=2 IF UNKNOWN  
LMK  
B=1 IF LMK COOR-  
DINATES ARE STUR-  
ED  
B=2 IF LMK COOR-  
DINATES ARE NOT  
STORED  
CD= LMK ID NO. N  
E=1 IF EARTH LMK  
E=2 IF LUNAR LMK

VII CHECK CMC FLASHES VERB-NOUN TO  
REQUEST RESPONSE AND DISPLAYS  
LMK DATA

FL VOS N70  
BLANK  
ABCDE  
BLANK

A=1 IF KNOWN LMK  
A=2 IF UNKNOWN LMK  
B=1 IF LMK COOR-  
DINATES ARE NOT  
STORED  
CD= LMK ID NO. N  
E=1 IF EARTH LMK  
E=2 IF LUNAR LMK

8

ACCEPT:  
PRO

IS THE DATA IN R2  
CORRECT FOR THIS  
SIGHTING?  
N  
Y

KEY IN V22E AND  
LOAD CORRECT  
DATA.

8

REJECT:  
LOAD DESIRED DATA.

8

WAIT FOR KEYBOARD  
ENTRY

TERMINATE FLASH UPON  
 RECEIPT OF PROCEED  
 OR NEW DATA

---

|     |     |
|-----|-----|
| • N | • P |
| • E | • R |
| • W | • D |
| • C | • C |
| • A | • E |
| • D | • E |
| • I | • D |
| • T | • A |
| • F | • T |
| • A | • A |

---

STORE NEW DATA

KEY IN PROCEED

8300

IS THE LAK KNOWN AND  
ARE ITS COORDINATES  
STORED?

70  
6320

4320

134

## VIII IF LANDMARK KNOWN BUT COORDINATES

P222/SUNDISK

159

422 / SUNDOK

|      |                 |
|------|-----------------|
| PUSA | FLASH VÉKB-NUUN |
| HGLU | TU KÉJÜCST RES- |
| •    | PULSE AND DIS-  |
| SNAP | PLAY LMK COOR-  |
| •    | DINATES:        |
|      | V06 N89         |
|      | R1-LAT          |
|      | R2-LLG/2        |
|      | R3-AIT          |

MONITOR DSKY;  
OBSERVE VERB-INDOUN  
FLASH TU REQUEST  
RESPONSE AND DISPLAY  
LINK COORDINATES

NOT STORED CHECK CMIC FLASHES VERB-  
NOUN TO REQUEST RESPONSE AND DIS-  
PLAYS LANDMARK COORDINATES.

AM I SATISFIED WITH  
THESE VALUES?

LAT-LATITUDE OF LANDMARK + 15  
NORTH

LONG/2-LONGITUDE OF LANDMARK  
DIVIDED BY TWO + IS EAST

1160

WAIT FUR KÉY-  
SCARO ENTRY

KEY IN PROCEED

REJECT : LOAD LANDMARK COORDINATES

KEY IN V2SE AND  
LOAD LMK PARAMETERS:  
1. LAT IS LATITUDE  
2. LMK IN DEG TO  
3. EAREST •001 DEGREE.  
4. IS NORTH

13-ALT IS ALTITUDE  
OF LMK ABOVE THE  
FISCHER ELLIPSOID IN  
NAUTICAL MILES TO  
THE NEAREST .01 NM.

TERMINATE FLASH  
UPON RECEIPT  
OF PROCEED OR  
NEW DATA

97

72

#410

#420

#43

SIGRE  
NEW  
DATA

SELECT FIRST  
SIGHTING MARK  
DATA

COMPUTE ORBITAL  
PARAMETER AND  
LANDMARK COOR-  
DINATE CHANGES  
AS A RESULT OF  
THIS SIGHTING  
MARK

POSS  
PKLU  
HOLD  
SNAP

FLASH VERB-NOUN TO  
REQUEST RESPONSE  
AND DISPLAY ORBI-  
TAL PARAMETER  
CHANGES:

VUG N49

R1 - DELTA K  
R2 - DELTA V  
R3 - BLANK

MONITOR DSKY:  
OBSERVE VERB-NOUN  
FLASH TO REQUEST RE-  
SPONSE AND DISPLAY  
OF ORBITAL PARAMETER  
CHANGES

CHECK CMC FLASHES VERB-NOUN TO  
REQUEST RESPONSE AND DISPLAYS  
ORBITAL PARAMETER CHANGES (2 DIS-  
PLAYS FOR EACH MARK)

FL V06 N49

DELTA R  
DELTA V  
BLANK

#440

DELTA R-MAGNITUDE  
OF THE DIFFER-  
ENCE BETWEEN  
THE POSITION  
VECTOR BEFORE  
AND AFTER IN-  
CORPORATION OF  
THE LANDMARK  
SIGHTING DATA.  
IN N.M. TO  
NEAREST 0.1 N.M.

DELTA R - MAGNITUDE OF THE  
DIFFERENCE BETWEEN THE POSI-  
TION VECTOR BEFORE AND AFTER  
INCORPORATION OF THE LANDMARK  
SIGHTING DATA.

DELTA V-MAGNITUDE  
OF THE DIFFER-  
ENCE BETWEEN  
THE VELOCITY  
VECTOR BEFORE  
AND AFTER IN-  
CORPORATION OF  
THE LANDMARK  
SIGHTING DATA.  
IN FPS TO NEAR-  
EST 0.1 FPS

DELTA V - MAGNITUDE OF THE DIFF-  
ERENCE BETWEEN THE VELOCITY  
VECTOR BEFORE AND AFTER INCOR-  
PORATION OF THE LANDMARK  
SIGHTING DATA.

#470

73

ARE ORBITAL  
PARAMETER CHANGES  
ACCEPTABLE FOR IN-  
SERTION INTO CMC  
CALCULATION OF  
POSITION AND  
VELOCITY

Y

N.

ACCEPT: PRO  
#490

REJECT: V34E  
#500

WAIT FOR KEYBOARD  
ENTRY

TERMINATE FLASH  
UPON RECEIPT OF  
PROCEED OR TERMINATE  
NATE

|   |   |
|---|---|
| P | T |
| R | E |
| S | K |
| L | M |
| C | L |

6510

HAVE THE ORBITAL  
PARAMETER  
CHANGES BEEN  
COMPUTED TWICE  
FOR THIS MARK

HAVE ALL THE  
MARKS BEEN PRO-  
CESSED

SELECT THE  
DATA FROM THE  
NEXT SIGHTING  
MARK

FLASH VERB-NOUN  
TU REQUEST PROCEED  
AND DISPLAY LANDMARK  
ID IN.  
VOS N70  
R1-BLANK  
R2-BLANK  
R3-BLANK

MONITOR DSKY:  
OBSERVE DISPLAY OF  
LMK ID NO. AT LOCA-  
TIONS CD OF R2

HULL - FLASH VERB-NOUN  
\*\*\* TU REQUEST PROCEED  
SNAP - AND DISPLAY LANDMARK  
ID IN.  
VOS N70  
R1-BLANK  
R2-BLANK  
R3-BLANK

CHECK CMC FLASHES VERB-NOUN TO  
REQUEST RESPONSE AND DISPLAYS  
LANDMARK ID NO.

FL VOS N70  
BLANK  
LANDMARK ID 00C00  
BLANK

IF DISPLAY OF LANDMARK COORDINATES

P22/SUNDISK

P22/SUNDISK

IS DESIRED:  
PRO

---

IF NOT:  
V34E  
GO TO STEP XII

#560

---

KEY IN  
TERMINATE  
V34E

WAIT FOR KEYBOARD ENTRY:

---

TERMINATE FLASH UPON RECEIPT OF PROCEEDED OR TERMINATE

---

Y. .PROCEEDED

E.

R.

N. FLASH VERB-NOUN  
N. TO REQUEST PRO-  
A. CEED AND DISPLAY

F. UPDATED LMK  
COORDINATES

E. V06 N89  
R1-LAT  
R2-LONG/2  
R3-ALT

ROSS  
HOLD  
SNAP

MONITOR DSKY:  
OBSERVE DISPLAY  
OF UPDATED LMK  
COORDINATES

FL V06 N89  
LAT XX.XXX DEG  
LONG/2 XX.XXX DEG  
ALT XXX.XX NM

RECORD DATA

XI

CHECK CMC FLASHES VERB-NOUN TO REQUEST RESPONSE AND DISPLAYS UPDATED LANDMARK COORDINATES

#580

75

---

RECORD DATA

SHALL THESE DATA BE SAVED IN CMC MEMORY?

---

N .Y

REJECT (DATA NOT TO BE STORED IN CMC): V34E

#590

---

WAIT FOR KEY-  
BOARD ENTRY

---

KEY IN  
TERMINATE  
V34E

#600

TERMINATE FLASH  
UPON RECEIPT OF  
PROCEED OR  
TERMINATE

KEY IN PROCEED

ACCEPT (DATA TO BE STORED IN CMC):  
PRO

T P  
E R  
R D  
M C  
I E  
N E  
A D  
T I  
E

#610

STOKE THESE  
COORDINATES  
AS UPDATED  
LINK PARAMET-  
TERS AND  
UPDATE NOUN  
TO INDIC-  
ATE STORED  
LINK AND LNK  
ID NO N.

#620

#630  
76

HOLD FLASH VERB-NOUN TO  
REQUEST PLEASE PER-  
FORM ADDITIONAL  
SNAP SIGHTING:  
VS0 N25  
R1-00017  
K2-BLANK  
K3-BLANK

XII CHECK CMC FLASHES VERB-NOUN TO  
REQUEST PLEASE PERFORM ADDITIONAL  
SIGHTINGS

#640  
FL V50 N25  
00017  
BLANK  
BLANK

ACCEPT: ENTR  
RETURN TO STEP V

DO I WANT TO PERFORM  
ANOTHER SIGHTING?  
N Y

#650  
REJECT: PRO  
PERFORM PROGRAM TERMINATION  
ROUTINE (R00).

WAIT FOR KEYBOARD  
ENTRY

KEY IN PROCEED

XIII SET:  
OPTICS MODE = ZERO

#22/SUNDISK

163 P22/SUNDISK

TERMINATE FLASH UPON  
RECEIPT OF ENTER OR  
PROCEED

G/N OPTICS PWR - OFF  
G/N PWR - OFF

6660

KEY IN  
ENTER

\*E \*P  
\*N \*R  
\*T \*O  
\*E \*C  
\*R \*E  
\*... \*D  
GO TO "A"  
ABOVE

DO ROUTINE R00  
"A"  
ABOVE

6670

DO ROUTINE R00

77  
6680

EXIT

CHANGE CONTROL NOTES

LOGIC REV 2B PCN M11 - 64


APPENDIX C

APOLLO 7 CREW CHECKLIST FOR P22

## SECTION 4. COAST

Basic Date — Aug. 18, 1967, Rev. Dec 22, 1967  
 Changed — May 1, 1968


CSM 101

P21 - CSM GRND TRK DETERMINATION  
CMC - ON(Req) pg 0/2-1P22-CSM-ORBITAL NAV LANDMARK TRACKING

CMC - ON(Req) pg 0/2-1  
 IMU - ON(Req) pg 0/2-1  
 SCS - ON(Req) pg 0/3-1  
 CMC ATT-IMU  
 .05G sw - OFF  
 SCS, LOGIC - BUS 3  
 G&N PWR OPTICS - ON  
 BMAG MODE (3) - RATE 2  
 OPTICS MODE - MAN  
 OPTICS MODE - ZERO (15 secs)

14. COAST

P21, 22, 23, 27



- 3 Select LMK  
 4 Perform ORDEAL INITIALIZATION pg 0/3-5

- 5 Move to sighting attitude  
 ESTABLISH ORBITAL RATE  
 RHC = ALCAN X<sub>SC</sub> 23° BELOW LOC HOR, SEF  
 HEADS UP (SHAFT AXIS IN ORBITAL PLANE  
 AND 10° FWD OF LOCAL VERTICAL)  
 RHC or HIC PITCH TO OFFSET ORB RATE,  
 ROLL TO AVOID SHAFT AXIS <10° OFF LMK

- 6 

|            |                        |
|------------|------------------------|
| FL V50 N25 | PERFORM                |
| RL 00011   | AUTO OPTICS POS option |

  
 OPTICS MODE-GMC                           OPTICS MODE MAN  
 ENTR                                       PRO → STEP 9
- 7 

|               |              |
|---------------|--------------|
| FL V06 N89    | LMK IDENTITY |
| LAT XX.XXX    | DEG (+NORTH) |
| LONG/2 XX.XXX | DEG (+EAST)  |
| ALT XXX.XX    | NM           |

  
 PRO                                       LDD  
   PRO → STEP 9
- |                     |               |
|---------------------|---------------|
| Possible FL V05 N09 |               |
| RL 00404            | TRUNNION >90° |

  
 MAN MNVR to acquire                   PRO → TERMINATE
- 8 

|                 |                     |
|-----------------|---------------------|
| V06 N92         | NEW OCDU ANG        |
| SHAFT XXX.XX    | DEG (DESIRED SHAFT) |
| TRUNNION XX.XXX | DEG (DESIRED TRUN)  |

  
 Possible PROGRAM ALARM lt (TRUN>38°)  
 MNVR to acquire LMK  
 OPTICS MODE - MANUAL  
 Establish proper pitch rate

Basic Date Aug. 18, 1967  
 Changed May 1, 1968

CS 01

1. COAST

4.


CSM 101


Basic Date — Aug. 18, 1967, Rev. Dec 22, 1967  
 Changed — May 1, 1968

83

4-3


P22





P23-CSM-CISLUNAR MIDCOURSE NAV MEASUREMENT PROGRAM

CMC - ON(Req) pg 0/2-1  
 G/N PWR OPTICS - ON (up)  
 CMC ATT - IMU  
 .05G sw - OFF  
 SCS LOGIC - BUS 3  
 OPTICS MODE - MAN  
 OPTICS MODE - ZERO (15 secs)  
 Move RHC to LEB  
 Select SC control  
 PERF STAR - LMK ACQ



Basic Date - Aug. 18, 1967.  
 Changed - May 1, 1968

CS: 01

APPENDIX D

SUNDISK P22 VERIFICATION TEST - TWO KNOWN LANDMARKS CASE

TABLE D-I.- DIFFERENCE BETWEEN THE BIT-BY-BIT  
AND THE ENGINEERING-SIMULATION UNIT b-VECTOR

| Mark no. | Incorporation no. | $b_1$      | $b_2$      | $b_3$      |
|----------|-------------------|------------|------------|------------|
| 1        | First             | .00010925  | .00039536  | -.00002127 |
|          | Second            | -.00002955 | .00012107  | .000000174 |
| 2        | First             | .00625410  | .000008850 | -.00000745 |
|          | Second            | .00000434  | -.00002697 | -.00000037 |
| 3        | First             | .00001870  | .00008554  | .00001657  |
|          | Second            | -.00001613 | -.00000897 | .00000034  |
| 4        | First             | .00005400  | .00006314  | -.00001012 |
|          | Second            | .00004329  | .00035168  | -.00000038 |
| 5        | First             | .00003496  | .00006639  | -.00000435 |
|          | Second            | -.00021332 | .00015567  | .00000072  |
| 1        | First             | .00006993  | .00029096  | -.00012903 |
|          | Second            | .000003    | -.00002593 | -.000012   |
| 2        | First             | -.00000597 | -.00016595 | -.00026864 |
|          | Second            | -.00001594 | .00004936  | .00000018  |
| 3        | First             | .00004537  | -.0000474  | -.00001425 |
|          | Second            | .01065872  | .00019926  | -.00005230 |

TABLE D-II.- THE BIT-BY-BIT UNIT  $b$ -VECTOR

| Mark no. | Incorporation no. | $b_1$      | $b_2$      | $b_3$      |
|----------|-------------------|------------|------------|------------|
| 1        | First             | .01722365  | .06601096  | -.99767023 |
|          | Second            | .96760445  | -.25247107 | -.00000018 |
| 2        | First             | .01692410  | .08906350  | -.99596855 |
|          | Second            | .99287134  | -.11919103 | .00000063  |
| 3        | First             | -.01325370 | .11024054  | -.99381657 |
|          | Second            | .99284787  | .11938646  | .00000234  |
| 4        | First             | -.06199400 | .11216514  | -.99175388 |
|          | Second            | .87520529  | .48375168  | .00000262  |
| 5        | First             | -.09830496 | .07236639  | -.99252165 |
|          | Second            | .59285168  | .80531167  | -.00000277 |
| 1        | First             | -.02082393 | .41681896  | -.90875097 |
|          | Second            | .99875302  | .04992407  | .00001247  |
| 2        | First             | -.10489403 | .44763405  | -.88804336 |
|          | Second            | .97362556  | .22815184  | .00000115  |
| 3        | First             | -.39230337 | .09168866  | -.91525475 |
|          | Second            | .23289772  | .97249826  | -.00240317 |

TABLE D-III.- THE BIT-BY-BIT VECTOR UPDATES

| Mark no. | $\underline{r}_c$ , ft |                 |                | $\underline{v}_c$ , fps |                |                | $\underline{x}_k$ , ft |                   |                   |
|----------|------------------------|-----------------|----------------|-------------------------|----------------|----------------|------------------------|-------------------|-------------------|
|          | X                      | Y               | Z              | $\dot{X}$               | $\dot{Y}$      | $\dot{Z}$      | X                      | Y                 | Z                 |
| 1        | -16.0<br>658.4         | -62.1<br>-171.8 | 940.0<br>0.0   | 0.0<br>0.0              | 0.0<br>0.0     | 0.0<br>0.0     | 115.3<br>4682.9        | 442.1<br>1222.0   | -6684.6<br>0.0    |
| 2        | -3.0<br>106.9          | -12.2<br>149.3  | 25.8<br>13.2   | -.0005<br>.0125         | -.0005<br>.003 | .006<br>.0009  | 20.2<br>-761.3         | 86.3<br>-1062.9   | -184.0<br>55.6    |
| 3        | -1.8<br>98.6           | -10.0<br>360.0  | 9.4<br>33.6    | .0005<br>.009           | -.0009<br>.007 | .0082<br>.0144 | 10.4<br>-697.7         | 72.5<br>-2562.8   | -65.5<br>-239.5   |
| 4        | 0.0<br>19.6            | -5.2<br>205.5   | 12.4<br>20.4   | .0019<br>-.0125         | .0029<br>.021  | .0260<br>.016  | -.4.4<br>-145.8        | 42.9<br>-1457.4   | -82.5<br>-143.4   |
| 5        | -1.6<br>-4.4           | 5.6<br>42.7     | 19.2<br>4.8    | .0019<br>-.0125         | .0039<br>.0154 | .0675<br>.004  | -8.1<br>21.6           | 16.8<br>-297.     | -116.1<br>-27.8   |
| 1        | -25.0<br>803.4         | -231.3<br>-72.1 | 661.6<br>-90.1 | -.152<br>.404           | .136<br>-.348  | .073<br>-.342  | -110.3<br>-5718.3      | 2210.7<br>-271.9  | -4819.7<br>-30.4  |
| 2        | 4<br>25.6              | -2.6<br>314.8   | .8<br>158.6    | .0010<br>-.148          | -.0010<br>.116 | -.0005<br>.123 | -2.0<br>-559.9         | 19.6<br>-2294.8   | -7.6<br>-1038.8   |
| 3        | -227.5<br>-56.1        | 642.4<br>152.4  | 425.3<br>69.1  | -.515<br>-.138          | .324<br>-.105  | .511<br>-.038  | 352.4<br>160.8         | -3991.3<br>-999.8 | -2356.5<br>-302.0 |

TABLE D-IV.- ENGINEERING-SIMULATION VECTOR UPDATES

| Mark no. | Simulation time | $\underline{r}_c$ , ft |                   |                  | $\underline{v}_c$ , fps |                    |                    | $\underline{x}_y$ , ft |                    |                    |
|----------|-----------------|------------------------|-------------------|------------------|-------------------------|--------------------|--------------------|------------------------|--------------------|--------------------|
|          |                 | X                      | Y                 | Z                | $\dot{X}$               | $\dot{Y}$          | $\dot{Z}$          | X                      | Y                  | Z                  |
| 1        | 4485.2604       | -17.21<br>668.83       | -66.01<br>-174.45 | 1003.82<br>0.00  | 0.000000<br>0.0         | 0.000000<br>0.0    | 0.000000<br>0.0    | 122.44<br>-4756.17     | 469.46<br>1240.54  | -7138.31<br>.00    |
| 2        | 4485.4561       | -3.19<br>108.81        | -13.46<br>151.17  | 28.58<br>13.08   | -.00132<br>0.01277      | 0.00131<br>-.00633 | 0.00611<br>-.00205 | 22.43<br>-772.61       | 96.17<br>-1076.28  | -202.84<br>-93.87  |
| 3        | 4485.6890       | -1.60<br>89.26         | -10.06<br>326.41  | 9.36<br>30.34    | -.0007<br>0.00661       | 0.00061<br>0.00515 | 0.00771<br>0.01168 | 10.52<br>-663.38       | 72.73<br>-2323.60  | -65.45<br>-216.76  |
| 4        | 4485.9463       | .0414<br>17.94         | -.57<br>188.69    | 13.51<br>19.13   | -.00069<br>-.01164      | 0.00076<br>0.02543 | 0.02644<br>0.02136 | -.4.98<br>-133.86      | 46.39<br>-1336.89  | -90.45<br>-131.24  |
| 5        | 4486.1872       | -1.08<br>-4.05         | 4.68<br>39.34     | 16.60<br>4.51    | -.00307<br>-.01395      | 0.00340<br>0.0188  | 0.05655<br>0.0087  | -7.27<br>20.01         | -15.87<br>-271.7   | -102.28<br>-25.60  |
| 1        | 4490.4128       | -25.58<br>790.47       | -252.6<br>-68.80  | 664.56<br>-86.33 | -.1614<br>0.3764        | 0.1426<br>-.3358   | 0.0803<br>-.3321   | -119.3<br>-5623.7      | 2394.25<br>-267.07 | -5224.78<br>-29.03 |
| 2        | 4490.6157       | -.4303<br>28.38        | 2.43<br>307.5     | -.6701<br>153.9  | 0.00090<br>-.1398       | 0.00074<br>0.108   | 0.00029<br>0.1134  | 1.94<br>-553.01        | -18.70<br>-2256.2  | 7.15<br>-1019.1    |
| 3        | 4491.2170       | -212.5<br>57.48        | 601.87<br>156.40  | 398.37<br>70.17  | -.496<br>-.1399         | 0.312<br>0.1035    | 0.470<br>0.0452    | 333.28<br>165.5        | -3726.5<br>-1024.5 | -2201.7<br>-310.23 |

TABLE D-V.- BIT-BY-BIT ESTIMATED  
LANDMARK POSITION

| Mark no.        | $r_l$ , ft   |             |             |
|-----------------|--------------|-------------|-------------|
|                 | X            | Y           | Z           |
| 1 Before inc. 1 | -11 915 844. | 12 998 932. | 11 228 431. |
| After inc. 2    | -11 920 412. | 13 000 596. | 11 221 747. |
| 2 After inc. 2  | -11 932 272. | 12 989 420. | 11 221 465. |
| 3 After inc. 2  | -11 946 187. | 12 974 770. | 11 221 155. |
| 4 After inc. 2  | -11 960 939. | 12 959 903. | 11 220 926. |
| 5 After inc. 2  | -11 974 579. | 12 946 970. | 11 220 790. |
| 1 Before inc. 1 | -16 714 688. | 7 377 763.3 | 10 167 490. |
| After inc. 2    | -16 720 517. | 7 379 702.1 | 10 163 640. |
| 2 After inc. 2  | -16 727 617. | 7 362 582.6 | 10 161 587. |
| 3 After inc. 2  | -16 746 419. | 7 313 567.1 | 10 158 936. |

TABLE D-VI.- ENGINEERING-SIMULATION ESTIMATED  
LANDMARK POSITION

| Mark no. | $\underline{r}_k$ , ft       |                               |                                 |
|----------|------------------------------|-------------------------------|---------------------------------|
|          | X                            | Y                             | Z                               |
| 1        | -11 915 826.<br>-11 920 460. | 12 998 456.<br>13 000 166.000 | 11 228 979.<br>11 221 841.33681 |
| 2        | -11 932 336.                 | 12 988 976.                   | 11 221 542.                     |
| 3        | -11 946 184.                 | 12 974 563.                   | 11 221 259.                     |
| 4        | -11 960 923.                 | 12 959 814.                   | 11 221 037.                     |
| 5        | -11 974 566.                 | 12 946 910.                   | 11 220 907.                     |
| 1        | -16 714 671.<br>-16 720 415. | 7 377 346.9<br>7 379 474.1    | 10 167 805.<br>10 162 551.      |
| 2        | -16 727 508.                 | 7 362 355.6                   | 10 161 539.                     |
| 3        | -16 746 321.                 | 7 313 570.4                   | 10 159 026.                     |

TABLE D-VII.- DIFFERENCE BETWEEN THE BIT-BY-BIT AND THE  
ENGINEERING-SIMULATION W-MATRIX AFTER THE SECOND INCORPORATION

| Component          | Mark 1     |            |            | Mark 5    |            |           |
|--------------------|------------|------------|------------|-----------|------------|-----------|
|                    | X          | Y          | Z          | X         | Y          | Z         |
| $\Delta W_0$ , ft  | -.01520    | -.03490    | -.06710    | -.04470   | .40780     | -.26240   |
| $\Delta W_4$ , fps | -.00000001 | -.00000001 | -.00000001 | -.000015  | .00069     | -.00068   |
| $\Delta W_8$ , ft  | -1.48140   | -.57540    | -1.98560   | -.78880   | 1.57070    | .11410    |
| Mark 2             |            |            |            |           |            |           |
| $\Delta W_0$ , ft  | .03320     | -.10390    | -.01080    | -16.11995 | 3.30407    | -15.87292 |
| $\Delta W_4$ , fps | .00000035  | -.00000022 | .00000077  | .00293018 | -.00008940 | .00247909 |
| $\Delta W_8$ , ft  | -1.97350   | -1.70300   | -2.01810   | -2.2003   | -2.3050    | -1.5308   |
| Mark 3             |            |            |            |           |            |           |
| $\Delta W_0$ , ft  | .02600     | -.34920    | .08300     | -16.1051  | 3.7657     | -15.823   |
| $\Delta W_4$ , fps | -.0000478  | -.0000446  | -.00018039 | .002760   | -.0013531  | .0005372  |
| $\Delta W_8$ , ft  | -1.35330   | -6.20020   | -2.10720   | -1.2660   | -3.6684    | -4.7142   |
| Mark 4             |            |            |            |           |            |           |
| $\Delta W_0$ , ft  | .03800     | -.05430    | -.33020    | -16.0613  | 2.9635     | -14.9107  |
| $\Delta W_4$ , fps | -.0001806  | .0000720   | -.00004136 | .0000667  | -.003838   | -.0005748 |
| $\Delta W_8$ , ft  | -1.2098080 | -2.5446    | -1.4757    | .6733000  | -3.7243    | -.7403    |

TABLE D-VIII.- DIFFERENCE BETWEEN THE BIT-BY-BIT AND THE  
ENGINEERING-SIMULATION W-MATRIX AFTER MARK 5, SECOND INCORPORATION

| Row | Column   |          |          |           |           |          |         |         |           |
|-----|----------|----------|----------|-----------|-----------|----------|---------|---------|-----------|
|     | 1        | 2        | 3        | 4         | 5         | 6        | 7       | 8       | 9         |
| 1   | 0        | -.24     | -.0554   | 0         | -.01179   | .030013  | .61     | .264    | 1.749569  |
| 2   | .224     | .4       | .283     | .2826     | .08       | -.05447  | -.153   | -.78    | 7.07284   |
| 3   | .407     | .2547    | -.3      | .00131    | -.02617   | -.11     | -.564   | -.9043  | 1.7       |
| 4   | -.000617 | .00438   | .008588  | .000113   | .00032675 | .001974  | .02344  | .015624 | .04937078 |
| 5   | .00399   | .006111  | .008874  | .00011    | .00069    | .0020455 | .057646 | -.00589 | .04312110 |
| 6   | .00427   | .009286  | .0013978 | .00030783 | .001077   | .00068   | .040694 | .05726  | -.01098   |
| 7   | .29      | .057     | -.47158  | -.5988    | .0024     | .04023   | -.7406  | .0551   | -.343     |
| 8   | -.05725  | .7704    | .22      | -.004     | .059      | .19746   | .21     | -1.56   | .6417     |
| 9   | -.042    | -.354436 | -.0886   | -.00034   | .020711   | -.192    | .251    | .500764 | .114      |

TABLE D-IX.- BIT-EY-BIT W-MATRIX AFTER MARK 5, SECOND INCORPORATION

| Row | Column   |          |         |           |           |           |          |         |          |
|-----|----------|----------|---------|-----------|-----------|-----------|----------|---------|----------|
|     | 1        | 2        | 3       | 4         | 5         | 6         | 7        | 8       | 9        |
| 1   | 2662.5   | 6.6128   | -2.1871 | 162.95    | -.45368   | .17522    | 895.36   | -36.374 | -8.8359  |
| 2   | -53.463  | 2667.9   | 9.8950  | -13.912   | 154.16    | .14236    | 125.55   | 887.57  | -8.1131  |
| 3   | -10.515  | 4.5900   | 2652.6  | -1.8288   | -.46151   | 159.03    | 13.556   | 4.3663  | 919.60   |
| 4   | .0024359 | -.22319  | .18501  | 3.0244    | -.0046193 | -.0065560 | .02662   | -.07097 | -.05119  |
| 5   | -.21635  | .02072   | .20895  | -.0065974 | 3.0233    | .0070080  | -.08832  | .09278  | .06768   |
| 6   | -.18657  | .21081   | -.09389 | -.0077541 | .0067707  | 3.0070    | -.04338  | .06229  | .14247   |
| 7   | 2381.05  | -.85.424 | -7.3575 | 37.170    | 3.6388    | 1.9180    | 1646.97  | 226.379 | 19.236   |
| 8   | 339.98   | 2357.77  | -40.991 | 98.035    | 99.660    | -5.1141   | -916.87  | 1702.25 | 110.855  |
| 9   | 39.639   | 4.5619   | 2434.49 | 11.807    | 3.5919    | 59.185    | -110.117 | -9.2364 | 1503.301 |

APPENDIX E

SUNDISK P22 VERIFICATION TEST - ONE KNOWN, ONE UNKNOWN LANDMARK CASE

TABLE E-I.- BIT-BY-BIT VECTOR UPDATES

| Mark no. | $\underline{r}_c$ , ft |        |       | $\underline{v}_c$ , fps |           |           | $\underline{r}_k$ , ft |         |         |
|----------|------------------------|--------|-------|-------------------------|-----------|-----------|------------------------|---------|---------|
|          | X                      | Y      | Z     | $\dot{X}$               | $\dot{Y}$ | $\dot{Z}$ | X                      | Y       | Z       |
| Known    |                        |        |       |                         |           |           |                        |         |         |
| 2        | 292.6                  | -35.2  | 0.0   | .0034                   | -.0059    | -.0048    | -700.3                 | 84.1    | 0.0     |
| 3        | 307.6                  | 622.4  | 60.9  | .0174                   | .0077     | .0154     | -736.1                 | -1492.2 | -145.0  |
| 4        | 84.9                   | 1222.3 | 126.6 | -.0405                  | .0810     | .0733     | -209.1                 | -2922.8 | -302.0  |
| 5        | -56.1                  | 377.3  | 40.9  | -.0482                  | .0637     | .0328     | 124.2                  | -893.9  | -90.5   |
| Unknown  |                        |        |       |                         |           |           |                        |         |         |
| 1        | 686.4                  | -68.5  | -77.7 | .3887                   | -.2923    | .2932     | 5880.8                 | -283.1  | -24.0   |
| 2        | 20.8                   | 264.3  | 131.4 | -.1157                  | .1100     | .1100     | -568.7                 | -2296.4 | -1039.7 |
| 3        | -32.4                  | 85.3   | 36.2  | -.0781                  | .0367     | .0183     | 106.5                  | -655.6  | -201.8  |

TABLE E-II.- ENGINEERING-SIMULATION VECTOR UPDATES

| Mark no. | Simulation time | $\underline{r}_c$ , ft |                   |                  | $\dot{\underline{r}}_c$ , fps |                     |                   | $\underline{r}_d$ , ft |                      |                       |
|----------|-----------------|------------------------|-------------------|------------------|-------------------------------|---------------------|-------------------|------------------------|----------------------|-----------------------|
|          |                 | X                      | Y                 | Z                | $\dot{X}$                     | $\dot{Y}$           | $\dot{Z}$         | X                      | Y                    | Z                     |
| Unknown  |                 |                        |                   |                  |                               |                     |                   |                        |                      |                       |
| 2        | 1485.4561       | .2003<br>309.48        | 1.643<br>-37.21   | -18.24<br>-.0436 | .000227<br>.003705            | -.000285<br>-.00602 | -.00014<br>-.0049 | -.473<br>740.56        | -3.94<br>88.89       | 43.899<br>-.032       |
| 3        | 1485.6890       | .1953<br>305.48        | 4.767<br>616.59   | -15.65<br>59.56  | .000667<br>.0163              | -.000698<br>.000397 | -.00241<br>.00717 | .3498<br>-730.07       | -.11.58<br>-1477.81  | 37.34<br>-143.728     |
| 4        | 1485.9463       | .7398<br>85.69         | -3.897<br>1223.6  | 13.23<br>127.44  | -.00083<br>-.0443             | .00085<br>.08038    | .0073<br>.0757    | -2.2567<br>209.7       | 10.077577<br>-2924.9 | -31.165889<br>-300.73 |
| 5        | 1486.1872       | -.1690<br>-56.88       | 7.716<br>381.08   | 33.82<br>41.35   | -.0465<br>-.055               | .00499<br>.07529    | .0409<br>.0474    | 3.39<br>126.6          | -13.77<br>-902.23    | 77.34<br>-90.90       |
| Known    |                 |                        |                   |                  |                               |                     |                   |                        |                      |                       |
| 1        | 1490.4128       | 22.27<br>688.65        | -262.29<br>-65.52 | 678.05<br>-75.05 | -.157<br>.389                 | .1199<br>-.285      | .1282<br>-.288    | -147.74<br>-5896.8     | 2955.4<br>-284.3     | -647.0<br>-23.28      |
| 2        | 1490.6157       | 1.0377<br>21.46        | -5.5764<br>228.9  | 1.5418<br>113.06 | .002156<br>-.096              | -.00211<br>.092     | -.0038<br>.093    | -5.255<br>-498.8       | 50.2<br>-2001.7      | -19.12<br>-904.6      |
| 3        | 1491.2170       | -162.62<br>-41.15      | 456.61<br>109.2   | 305.6<br>45.84   | -.374<br>-.099                | .254<br>.079        | .387<br>.029      | 311.36<br>136.7        | -3559.3<br>-837.4    | -1992.8<br>-258.4     |

TABLE E-III.- BIT-BY-BIT ESTIMATED LANDMARK POSITION

| Mark no.        | $r_l$ , ft   |             |             |
|-----------------|--------------|-------------|-------------|
|                 | X            | Y           | Z           |
| Unknown         |              |             |             |
| 2 Before Inc. 1 | -11 931 967. | 12 992 613. | 11 220 524. |
| After Inc. 2    | -11 932 667. | 12 992 693. | 11 220 577. |
| 3 After Inc. 2  | -11 946 634. | 12 979 028. | 11 220 454. |
| 4 After Inc. 2  | -11 961 449. | 12 962 645. | 11 220 120. |
| 5 After Inc. 2  | -11 974 998. | 12 949 119. | 11 219 936. |
| Known           |              |             |             |
| 1 Before Inc. 1 | -16 714 688. | 7 377 776.1 | 10 167 490. |
| After Inc. 2    | -16 720 707. | 7 380 254.0 | 10 161 428. |
| 2 After Inc. 2  | -16 727 834. | 7 363 162.1 | 10 160 369. |
| 3 After Inc. 2  | -16 746 721. | 7 315 078.5 | 10 158 148. |

TABLE E-IV.- ENGINEERING-SIMULATION  
ESTIMATED LANDMARK POSITION

| Mark no. | $r_l$ , ft                   |                            |                            |
|----------|------------------------------|----------------------------|----------------------------|
|          | X                            | Y                          | Z                          |
| Unknown  |                              |                            |                            |
| 2        | -11 931 917.<br>-11 932 656. | 12 992 613.<br>12 992 689. | 11 220 566.<br>11 220 609. |
| 3        | -11 946 618.                 | 12 979 045.                | 11 220 501.                |
| 4        | -11 961 434.                 | 12 962 673.                | 11 220 168.                |
| 5        | -11 974 969.                 | 12 949 141.                | 11 219 999.                |
| Known    |                              |                            |                            |
| 1        | -16 714 671.<br>-16 720 716. | 7 377 346.9<br>7 380 018.0 | 10 167 805.<br>10 161 313. |
| 2        | -16 727 763.                 | 7 363 222.7                | 10 160 388.                |
| 3        | -16 746 629.                 | 7 314 991.9                | 10 158 136.                |

TABLE E-V.- DIFFERENCE BETWEEN THE BIT-BY-BIT AND THE ENGINEERING-SIMULATION ESTIMATED POSITION AND VELOCITY VECTOR

| Mark no. | Time of state vector computation | $\Delta r_c$ , ft |            |            | $\Delta v_c$ , fps |                  |                  |
|----------|----------------------------------|-------------------|------------|------------|--------------------|------------------|------------------|
|          |                                  | $\Delta X$        | $\Delta Y$ | $\Delta Z$ | $\Delta \dot{X}$   | $\Delta \dot{Y}$ | $\Delta \dot{Z}$ |
|          | Initialization                   | 0.0               | 0.0        | 0.0        | 0.0                | 0.0              | 0.0              |
| Unknown  |                                  |                   |            |            |                    |                  |                  |
| 2        | Before incorp.                   | 2.0               | 2.0        | -6.0       | -.002              | .005             | .008             |
| 3        | After second incorp.             | 6.0               | 24.0       | -2.0       | -.024              | .029             | .024             |
| 5        | After second incorp.             | -44.0             | 26.0       | -3.0       | .046               | -.042            | -.028            |
| Known    |                                  |                   |            |            |                    |                  |                  |
| 1        | Before incorp.                   | 11.6              | 2.0        | 2.0        | -.016              | -.004            | .002             |
| 3        | After second incorp.             | 17.0              | 78.7       | -30.       | -.022              | .005             | .040             |

TABLE E-VI.- DIFFERENCE IN THE RESIDUALS (ACTUAL  
 MINUS ESTIMATED) OF THE BIT-BY-BIT AND THE  
 ENGINEERING-SIMULATED POSITION AND VELOCITY VECTOR

| Mark no. | Time of state vector computation | $\delta r_c$ , ft |            |            | $\delta v_c$ , fps |                  |                  |
|----------|----------------------------------|-------------------|------------|------------|--------------------|------------------|------------------|
|          |                                  | $\Delta X$        | $\Delta Y$ | $\Delta Z$ | $\Delta \dot{X}$   | $\Delta \dot{Y}$ | $\Delta \dot{Z}$ |
|          | Initialization                   | 0.0               | 0.0        | 0.0        | 0.0                | 0.0              | 0.0              |
| Unknown  |                                  |                   |            |            |                    |                  |                  |
| 2        | Before incorp.                   | -2.6              | -2.0       | 7.0        | -.232              | -.005            | .0006            |
|          | After second incorp.             | 13.0              | -4.7       | 7.0        | .002               | -.005            | -.0006           |
| 5        | After second incorp.             | 43.4              | -31.4      | 41.6       | -.095              | .010             | .006             |
| Known    |                                  |                   |            |            |                    |                  |                  |
| 1        | Before incorp.                   | 10.0              | -1.7       | 2.0        | -.017              | .004             | -.017            |
|          | After second incorp.             | 14.0              | 20.0       | 47.0       | .021               | .011             | .015             |
| 3        | After second incorp.             | 17.0              | -76.       | 31.        | -.019              | -.007            | -.040            |

TABLE E-VII.- DIFFERENCE IN THE DIAGONAL OF THE BIT-BY-BIT  
AND THE ENGINEERING-SIMULATION W-MATRIX

| Mark no | Time of state vector computation | $\Delta r_c$ , ft |            |            | $\Delta v_c$ , fps |                  |                  | $\Delta r_g$ , ft |            |            |
|---------|----------------------------------|-------------------|------------|------------|--------------------|------------------|------------------|-------------------|------------|------------|
|         |                                  | $\Delta X$        | $\Delta Y$ | $\Delta Z$ | $\dot{\Delta X}$   | $\dot{\Delta Y}$ | $\dot{\Delta Z}$ | $\Delta X$        | $\Delta Y$ | $\Delta Z$ |
|         | Initialization                   | 0                 | 0          | 0          | 0                  | 0                | 0                | 0.0               | 0.0        | 0.0        |
| Unknown |                                  |                   |            |            |                    |                  |                  |                   |            |            |
| 1       |                                  | 0                 | 0          | 0          | 0                  | 0                | 0                | 0.0               | 0.0        | 0.0        |
| 2       |                                  | -.112             | .005       | -.139      | .86 E-4            | .14 E-4          | .03 E-4          | 2283.             | 32.89      | -.802      |
| 3       |                                  | -.012             | -.027      | .198       | .66 E-4            | .51 E-4          | .29 E-4          | -1.18             | -.531      | -.582      |
| 4       |                                  | .028              | -.204      | -.609      | 1.9 E-4            | 1.4 E-4          | 3.6 E-4          | -1.05             | -2.01      | -.956      |
| 5       |                                  |                   |            |            |                    |                  |                  |                   |            |            |
| Known   |                                  |                   |            |            |                    |                  |                  |                   |            |            |
| 1       |                                  | -17.9             | -.357      | -19.7      | 28.2 E-4           | 2.1 E-4          | 16.2 E-4         | -2.28             | -2.26      | -1.47      |
| 2       |                                  | -17.8             | .324       | -19.7      | 26.6 E-4           | -6.01 E-4        | 10.7 E-4         | -.629             | -4.50      | -3.86      |
| 3       |                                  | -17.7             | -.174      | -18.7      | 4.07 E-4           | 21.2 E-4         | .76 E-4          | 1.18              | -3.74      | .902       |

TABLE E-VIII.- DIAGONAL VALUES AT SPECIFIED  
POINTS IN THE BIT-BY-BIT W-MATRIX

| Mark no.      | Time state vector computation | $\underline{r}_c$ , ft |        |        | $\underline{v}_c$ , fps |           |           | $\underline{r}_l$ , ft |        |        |
|---------------|-------------------------------|------------------------|--------|--------|-------------------------|-----------|-----------|------------------------|--------|--------|
|               |                               | X                      | Y      | Z      | $\dot{X}$               | $\dot{Y}$ | $\dot{Z}$ | X                      | Y      | Z      |
|               | Initialization                | 2998.9                 | 2998.9 | 2998.9 | 3.0248                  | 3.0248    | 3.0248    | 4639.3                 | 4639.3 | 4639.3 |
| Unknown       |                               |                        |        |        |                         |           |           |                        |        |        |
| 3             |                               | 2283.9                 | 2853.9 | 2289.3 | 3.0242                  | 3.0252    | 3.02372   | 1992.6                 | 4099.7 | 2012.8 |
| Known         |                               |                        |        |        |                         |           |           |                        |        |        |
| 1 Before inc. |                               | -180.                  | 949.   | -170.  | -.9446                  | -.1558    | -.9459    | 7997.                  | 7997.  | 7997.  |
| 1 After inc.  |                               | -164.                  | 942.   | -158.  | -.9037                  | -.1436    | -.8555    | 2303.                  | 6986.  | 3227.  |
| 3 After inc.  |                               | -162.                  | 991.   | -164.  | -1.021                  | -.3573    | -1.038    | 1811.                  | 1628.  | 1527.  |

## REFERENCES

1. MIT: Guidance System Operations Plan for Manned CM Earth Orbital Missions Using Program Sundisk, Section 5, Guidance Equations (Rev. 2). MIT Instrumentation Laboratory, March 1968.
2. TRW: Programmed Guidance Equations for Sundisk Command Module Earth Orbital Program, Revision 1, based on DISK 282 Program. TRW/Houston, NAS 9-4816, February 25, 1968.
3. Clifford, J. B., Jr.: Apollo Coasting Flight Navigation Simulation - OBSIM/NAVSIM Program Formulation. TRW note no. 67-FMT-531, July 25, 1967.
4. Phillips, Laurel A.: Apollo Onboard Orbit Determination Equations. MSC memorandum no. 66-FM42-228, August 4, 1966.
5. Guidance System Operations Plan for Manned CM Earth Orbital Missions Using Program SUNDISK, Section 4, GNCS Operational Modes (Rev. 2). June 1968.
6. Kimball, Garner R.: Additional Sundisk Program Notes. MSC Draft for Corrections to Sundisk Program Notes, July 8, 1968.
7. Fox, M.: Discrepancy Report Status (June 28, 1968). TRW memorandum no. 68:7252.1-99, July 9, 1968.
8. Kimball, Garner R.: Updated Sundisk Program Notes and Discrepancies. MSC memorandum, May 18, 1968.
9. Flight Crew Support Division, Spacecraft Systems Branch: Crew Check List, Apollo 7. May 1, 1968.
10. Olah, G. T.: Sundisk P22 (Orbital Navigation) Verification. TRW memorandum draft, September 1968.